



VOLTCRAFT®

VOLTCRAFT® - TOP PERFORMANCE IN EVERY WAY

“Since 1982, our product range has been dynamically adapting to the constant changes in the industry. We commit to offering first-class quality to our customers while delivering an excellent cost-performance ratio. This philosophy remains the cornerstone of Voltcraft’s success.”

AT-200

DIGITAL MULTIMETER

N° 121502

CE

VERSION 12/21

With its extra functions, the AT-200 robust multimeter is ideal for working on motor vehicle circuits. In addition to the standard measurement functions, you can use an inductive pick-up to measure the speed of engines, with or without the distributor, or check the dwell angle. Additionally with temperature measurement.

HIGHLIGHTS

CAT III 250 V //

Engine revolutions measurement //

Diagnosis of electrical injection and ignition //

Data Hold & relative measurement //

Auto power off //

Secure current measurement inputs //

Overload protection in all measurement ranges //



TECHNICAL DATA

Display	3 3/4-digit LCD
Speed of measurement	2 measurements / sec.
Input resistance	approx. 10M Ω
Battery replacement symbol	<7.5V +/- 0,5V
Acoustic signal	for each button activation
Battery required	9V compound battery, NEDA 1604 or 006P type
Operating temperature	0°C to 50°C
Storage temperature	-20°C to 60°C
Rel. air humidity	< 70% (non-condensing)
Operating height	up to a max. 2,000 m above MSL
Temp. for guaranteed accuracy	+18°C to +28°C
Weight (incl. battery)	approx. 220 g
Dimensions (LxWxH)	146 x 66 x 41 (mm)

Type of operation	Measuring range	Accuracy	Resolution
DC Volt	400 mV	$\pm(0.8\%+3\text{dgt})$	0.1 mV
	4 V	$\pm(1.5\%+3\text{dgt})$	0.001 V
	40 V	$\pm(1.5\%+3\text{dgt})$	0.01 V
	400 V	$\pm(1.5\%+3\text{dgt})$	0.1 V
	600 V	$\pm(2.0\%+5\text{dgt})$	1 V
Overload protection: 600 V; input resistance: 10 M Ω			
AC Volt	400 mV	$\pm(1,8\%+40\text{dgt})$	0.1 mV
	4 V	$\pm(1.3\%+3\text{dgt})$	0.001 V
	40 V	$\pm(1.8\%+3\text{dgt})$	0.01 V
	400 V	$\pm(1.8\%+3\text{dgt})$	0.1 V
	600 V	$\pm(2.5\%+6\text{dgt})$	1 V
Overload protection: 600 V; input resistance: 10 M Ω			
No auto range in the 400 mV range			
Frequency of the alternating voltage: 50 Hz to 400 Hz			
DC Ampere	400 μ A	$\pm(1.0\%+3\text{dgt})$	0.1 μ A
	4000 μ A	$\pm(1.5\%+3\text{dgt})$	1 μ A
	40 mA	$\pm(1.5\%+3\text{dgt})$	0.01 mA

PACKAGE CONTENT

Digital Multimeter AT-200 // 9 V block // Rubber holster // Safety measurement cables // 2 Alligator clip // K-type thermo-sensor // Revolutions sensor // Operating instructions

This data sheet is published by Conrad Electronic SE, Klaus-Conrad-Str. 1, D-92240 Hirschau (www.conrad.com).

All rights including translation reserved. Reproduction by any method, e.g. photocopy, microfilming, or the capture in electronic data processing systems require the prior written approval by the editor. Reprinting, also in part, is prohibited. This data sheet represents the technical status at the time of printing.