

Dimmerliste für Artikel: 400028 LED MiniGlobe 5,5W (40W) 220-240V E14 470lm 180° 2700K DIM

Dimmertyp	max_LED
Berker-2875 60-600W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Berker-283010	1-5x5,5W, 1-6x7W, 1-6x10W, 1-4x13W
Berker-286610	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Berker-286710 20-360W	1-5x5,5W, 1-6x7W, 1-6x10W, 1-4x13W
Busch-Jäger 2200 60-400W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Busch-Jäger 2247U	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Busch-Jäger 2250U	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Busch-Jäger 6513 U102	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Gira-0302 00/I01 60-600W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Gira-0307 007I02 20-525W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Gira-1176 00/I01	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Gira-2262 00/I01 20-500W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Gira-118400	1-5x5,5W, 1-6x7W, 1-6x10W, 1-4x13W
Jung-0244020300-60-400W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Jung-243EX 20-360W	1-5x5,5W, 1-6x7W, 1-6x10W, 1-4x13W
Jung-254 DU IEI	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Jung-266 G DE-60-600W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
Lauritz Knudsen-506DA109 20-300W	1-5x5,5W, 1-6x7W, 1-6x10W, 1-4x13W
Lauritz Knudsen-506DA116 20-300W	1-5x5,5W, 1-6x7W, 1-6x10W, 1-4x13W
Merten SBD400R-1 40-400W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W
PEHA-433 60-300W	1-5x5,5W, 1-6x7W, 1-6x10W, 1-4x13W
PEHA-433HAB 20-315W	1-5x5,5W, 1-6x7W, 1-6x10W, 1-4x13W
PEHA-435HAB 60-600W	1-6x5,5W, 1-8x7W, 1-8x10W, 1-6x13W