

Operating instructions Scanner Aerial – Gigastick B116A -

SCANSTICK is a reception aerial for scanners appropriate for many frequency bands. The aerial is weather-resistant, waterproof and suitable for indoor and outdoor mounting.

MOUNTING:

First turn the three radials into the head of the aerial.

Indoor mounting: place the aerial as high as possible in the house, for example in the attic room. Connect the aerial with a 50 Ohm coaxial cable. At the side of the aerial you connect a coaxial N connector.

Outdoor mounting: Lead the cable through the aerial mast with a diameter between 26 and 38mm. Fix the cable to the aerial and place the aerial on the aerial mast. Because the head falls over the aerial mast the coaxial cable with connector will be waterproofly closed. You can also use the pipe and clamps to mount the antenna on. The pipe has to be mounted beside the mast. Use here as well the coaxial cable 50 Ohm with N connector.

Frequency	30-88, 108-174, 380-512, 800-1300MHz
Impedance	50 Ohm
Connector	N-type
Gain	3dB

