

JDYX.E56092 Fuses, Supplemental

[Page Bottom](#)

Fuses, Supplemental

[See General Information for Fuses, Supplemental](#)

WALTER ELECTRONIC CO LTD

E56092

2ND FL
97 CHUNG KING N RD, SEC 4
TAIPEI CITY, TAIWAN



Trademark and/or Tradename: "Walter", ,

Supplemental fuses: pigtail leads, cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
BFP	4.6 x 15.2 (0.18 x 0.60)	0.1 - 1.0	125Vac	10000
		0.1 - 1.0	250Vac	35
		1.1 - 3.5	125Vac	10000
		1.1 - 3.5	250Vac	100
		3.6 - 7.0	125Vac	10000
		3.0	300Vac	50
BTP	4.6 x 15.2 (0.18 x 0.60)	0.1 - 7.0	125Vac	10000
		0.1 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 7.0	250Vac	200
CLP	6.35 x 31.8 (0.25 x 1.25)	0.01 - 0.8	125Vac	10000
		0.01 - 0.8	250Vac	35
		1.0 - 2.5	125Vac	10000
CSP	5.2 x 20 (0.20 x 0.79)	0.01 - 7.0	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 5.0	250Vac	200
MDP	6.4 x 33 (0.25 x 1.30)	0.01 - 15	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.60 - 8.0	250Vac	200
		0.01 - 15	125Vdc	500
MGP	6.35 x 31.75 (0.25 x 1.25)	0.01 - 15	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.10 - 3.5	250Vac	100
		3.60 - 10	250Vac	200
SBP		0.125 - 3.5	125Vac	10000

	5.2 x 15.2 (0.20 x 0.60)			
		0.125 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		0.125 - 3.5	350Vac	100
SCP	5.2 x 20 (0.20 x 0.79)	0.1 - 10	125Vac	10000
		0.1 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 5.0	250Vac	200
		6 - 10	250Vac	200
SGP	5.2 x 20 (0.20 x 0.79)	0.01 - 10	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 10	250Vac	200
SIP	5.2 x 20 (0.20 x 0.79)	0.1 - 5.0	125Vac	10000
		0.1 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 5.0	250Vac	200
		0.1 - 5.0	125Vdc	100
SLA	5.3 x 20.2 (0.21 x 0.80)	3.15 - 7	125Vac	10000
		0.01 - 3	125Vac	10000
		0.01 - 1	250Vac	35
		1.1 - 3	250Vac	100
TLP	6.35 x 31.8 (0.25 x 1.25)	0.01 - 4.0	125Vac	10000
		5.0	125Vac	10000
		5.0	250Vac	200
TSP	5.2 x 20 (0.20 x 0.79)	0.01 - 3.5	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		4.0 - 5.0	125Vac	10000

Supplemental fuses: cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
BGF	4.6 x 15.2 (0.18 x 0.60)	0.1 - 1.0	125Vac	10000
		0.1 - 1.0	250Vac	35
		1.1 - 3.5	125Vac	10000
		1.1 - 3.5	250Vac	100
		3.6 - 7.0	125Vac	10000
BGT	4.6 x 15.2 (0.18 x 0.60)	0.1 - 7.0	125Vac	10000
		0.1 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 7.0	250Vac	200
CIL	6.35 x 31.8 (0.25 x 1.25)	0.01 - 0.8	125Vac	10000
		0.01 - 0.8	250Vac	35
		1.0 - 2.5	125Vac	10000

CIS	5.2 x 20 (0.20 x 0.79)	0.01 - 10	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.10 - 3.5	250Vac	100
		3.60 - 5.0	250Vac	200
MDC	6.4 x 33 (0.25 x 1.30)	0.01 - 15	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.60 - 8.0	250Vac	200
		0.01 - 15	125Vdc	500
MGC	6.35 x 31.75 (0.25 x 1.25)	0.01 - 15	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.10 - 3.5	250Vac	100
		3.60 - 10	250Vac	200
SBC	5.2 x 15.2 (0.20 x 0.60)	0.125 - 3.5	125Vac	10000
		0.125 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		0.125 - 3.5	350Vac	100
SCC	5.2 x 20 (0.20 x 0.79)	0.1 - 10	125Vac	10000
		0.1 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 5.0	250Vac	200
		6 - 10	250Vac	200
SGA	5.3 x 20.2 (0.21 x 0.80)	3.15 - 7	125Vac	10000
		0.01 - 3	125Vac	10000
		0.01 - 1	250Vac	35
		1.1 - 3	250Vac	100
SGC	5.2 x 20 (0.20 x 0.79)	0.01 - 10	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 10	250Vac	200
SIC	5.2 x 20 (0.20 x 0.79)	0.1 - 7.0	125Vac	10000
		0.1 - 7.0	125Vdc	100
		0.1 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
		3.6 - 7.0	250Vac	200
STC	5.2 x 20 (0.20 x 0.79)	0.01 - 7.0	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.10 - 3.5	250Vac	100
		3.6 - 7.0	250Vac	200
TDL	6.35 x 31.8 (0.25 x 1.25)	0.01 - 4.0	125Vac	10000
		5.0	125Vac	10000
		5.0	250Vac	200
TDS	5.2 x 20 (0.20 x 0.79)	0.01 - 3.5	125Vac	10000

		4.0 - 5.0	125Vac	10000
		0.01 - 1.0	250Vac	35
		1.1 - 3.5	250Vac	100
TDS-1A	5.2 x 20 (0.20 x 0.79)	1	125Vac	10000
		1	250Vac	35
TDS-4A	5.2 x 20 (0.20 x 0.79)	4	125Vac	10000

Supplemental micro fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
6125F	6.1 x 2.5 x 2.5 (0.24 x 0.10 x 0.10)	0.25 - 15.0	125Vac	50
		0.25 - 15.0	63Vdc	300
6125T	6.1 x 2.5 x 2.5 (0.24 x 0.10 x 0.10)	0.2 - 7.0	125Vac	50
		0.2 - 6.3	125Vdc	50
		7.0	63Vdc	50
TSA	3.6 x 10 (0.14 x 0.39)	0.01 - 0.63	125Vac	50
		0.01 - 0.63	250Vac	35
		1.0 - 6.3	250Vac	50
TSA(1.0A to 6.3A)	3.6 x 10 (0.14 x 0.39)	1.0 - 6.3	250Vac	50
		1.0 - 6.3	125Vac	50

Supplemental micro fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
FAP	3.6 x 10 (0.14 x 0.39)	0.01 - 0.63	125Vac	50
		0.01 - 0.63	250Vac	35
		0.7 - 6.3	125Vac	50
		0.7 - 6.3	250Vac	50
FCP	3.0 x 7.3 (0.12 x 0.29)	0.16 - 6.3	125Vac	50
		0.16 - 6.3	125Vdc	50
FIP	3.6 x 10 (0.14 x 0.39)	0.25 - 6.3	250Vac	50
FUP	3.6 x 10 (0.14 x 0.39)	0.3	250Vac	50
TCP	3.0 x 7.3 (0.12 x 0.29)	0.16 - 6.3	125Vac	50
		0.16 - 6.3	125Vdc	50

Supplemental micro fuses: pigtail leads, cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
ICP	3.6 x 10 (0.14 x 0.39)	0.1 - 6.3	250Vac	50
		0.1 - 6.3	125Vac	50
TAP	3.6 x 10 (0.14 x 0.39)	0.1 - 6.3	250Vac	50
		0.1 - 6.3	125Vac	50

Supplemental micro fuses: pigtail leads, filled-tube

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
----------	-------------	----------	-----------	-------------------------

2001	8.2 x 7 x 0.85 (0.32 x 0.28 x 0.03)	0.1 - 6.3	125Vac	50
		0.1 - 6.3	250Vac	50

Last Updated on 2015-07-06

[Questions?](#)

[Print this page](#)

[Terms of Use](#)

[Page Top](#)

© 2016 UL LLC

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2016 UL LLC".