

## 623 Bulkhead connector

insulation insert Code 0° housing code 1 flange mount /Flange 25x25

## **Technical Data**

number of pins

-20 °C to 130 °C temperature range protection type

when connected IP 66/67

**Electrical Data** signal rated current rated voltage max. 7 A\* 125 V (AC/DC) rated insulation voltage (L-L) 2000 V

mating cycles 500

## Data according to VDE 0110/EN61984, Paragraph 6.19.2.2

pollution degree over voltage category TTT max. height for operation 2000 m

**Material** 

zinc diecast / nickel plated

insulation insert PBT, UL 94 / V0

seals Contacts (not part of product contents)

Tools (not part of product contents)

A DF A 014 NN 00 00 0101 000



**Contact Arrangement** mating view




© 2018 TE Connectivity

TE Connectivity, TE connectivity (logo), intercontec (logo) and speedtec are trademarks.

While TE Connectivity (TE) has made every reasonable effort to ensure the accuracy of the information in this presentation, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this article are for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Specifications are subject to change without notice. Sometime to the latest dimensions and design specifications.

TE Connectivity Industrial GmbH Bernrieder Straße 15 94559 Niederwinkling, Deutschland Tel.: +49 9962 2002-0 Fax: +49 9962 2002-70 E-Mall: intercontec@te.com Web: www.intercontec.biz





Bei Bohrung M3 Sonderschraube mit dünnem Kopfdurchmesser verwenden, siehe Zubehör! Alternativ auch Gewinde M2,5 möglich

for M3 bore use special screw thin head diameter, see access possible also with tread M2.5

**Main Dimensions** Bulkhead connector

\*for max. wire cross-section pay attention to the cross-section of used contacts