Data sheet

6DL1133-6EW00-0PH1



SIMATIC ET 200SP HA, configurable I/O module, Al-DI16/DQ16X24VDC HART, suitable for terminal block H1, M1, color code CC00, channel diagnostics, 16-bit, +/-0.1%.

General information	
Product type designation	AI-DI 16/DQ 16x24VDC HART HA
Firmware version	V1.1
 FW update possible 	Yes
Usable terminal block	TB type H1, M1 and N0
Color code for module-specific color identification plate	CC00
Product function	
● I&M data	Yes; I&M0 to I&M3
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V16
 STEP 7 configurable/integrated from version 	V5.6
 PCS 7 configurable/integrated from version 	V9.0
 PCS neo can be configured/integrated from version 	V3.0
 PROFINET from GSD version/GSD revision 	GSDML V2.3
Operating mode	
• DI	Yes
Counter	Yes
• DQ	Yes
 DQ with energy-saving function 	No
• PWM	No
 Oversampling 	No
• MSI	No
• MSO	No
Redundancy	
 Redundancy capability 	Yes; With TB type M1
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption (rated value)	80 mA; without sensor supply
Current consumption, max.	90 mA; without sensor supply
Encoder supply	
Number of outputs	16
Output voltage, min.	18.2 V
Short-circuit protection	Yes; per channel, electronic
24 V encoder supply	

• 24 V	Yes
Short-circuit protection	Yes; Electronic (response threshold 0.7 A to 1.5 A)
 Output current per channel, max. 	0.5 A
Output current per module, max.	2 A
Power loss	
Power loss, typ.	4.5 W; without sensor supply
Address area	
Address space per module	
 Address space per module in mixed operation, max. 	42 byte; 34 bytes for inputs, 2 bytes for outputs and 6 bytes for QI information
 Address space per module in mixed operation with HART, max. 	82 byte; 34-byte inputs, 2-byte outputs, 40 bytes for HART secondary variables, and 6 bytes for QI information
 Address space per module in mixed operation with multiHART, max. 	70 byte; 34-byte inputs, 2-byte outputs, 24-byte HART inputs, 4-byte HART outputs, and 6 bytes for QI information
 Address space per module in purely digital operation, max. 	26 byte; 2 bytes for inputs, 2 bytes for outputs, 18 bytes for high-precision time stamping and 4 bytes for QI information.
 Address space per module in purely digital operation with counter/frequency measurement, max. 	88 byte; 2 bytes for inputs, 2 bytes for outputs, 40 bytes for counter input data, 40 bytes for counter output data and 4 bytes for QI information.
Digital inputs	
Number of digital inputs	16
Digital inputs, parameterizable	Yes
Source/sink input	Yes; P-reading
Input characteristic curve in accordance with IEC 61131, type 1	Yes
Input characteristic curve in accordance with IEC 61131, type 2	No
Input characteristic curve in accordance with IEC 61131, type 3	Yes
Pulse extension	Yes; off, 50 ms, 100 ms, 200 ms, 500 ms, 1 s, 2 s
Time stamping	Yes; Resolution 10 ms
Time stamp (with precision of 1 ms)	Yes; Resolution 1ms
Digital input functions, parameterizable	
Gate start/stop	Yes; Partner channel of n+8 counter
Freely usable digital input	Yes; Parameterizable input filter
• Counter	Yes; Incl. frequency measurement
— Number, max.	8; Counter channel n=0 7
— Counting frequency, max.	5 kHz
— Counting width	32 bit; Without sign
Counting direction up/down	Yes; Up
Input voltage	
Rated value (DC)	24 V
• for signal "0"	-30 to +5 V
• for signal "1"	+11 to +30V
Input current	
• for signal "1", typ.	2.5 mA
Input delay (for rated value of input voltage)	
for standard inputs	
— parameterizable	Yes; 0.05 / 0.1 / 0.4 / 0.8 / 1.6 / 3.2 / 12.8 / 20 ms (in each case + delay of 30 to
F	500 μs, depending on line length)
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m
Digital outputs	
Number of digital outputs	16
Current-sinking	No
Current-sourcing	Yes
Short-circuit protection	Yes; Response threshold 0.7 A to 1.3 A
Open-circuit detection	Yes
Overload protection	Yes
Limitation of inductive shutdown voltage to	L+ -(37 to 41V)
Controlling a digital input	Yes
Switching capacity of the outputs	
with resistive load, max.	0.5 A
• on lamp load, max.	5 W
Load resistance range	
Load resistance range	

• upper limit	12 kΩ
Output current	12.132
for signal "1" rated value	0.5 A
for signal "0" residual current, max.	0.7 mA
Output delay with resistive load	
• "0" to "1", typ.	50 µs
• "1" to "0", typ.	100 μs
Parallel switching of two outputs	
• for uprating	No
for redundant control of a load	Yes
Switching frequency	
with resistive load, max.	100 Hz
on lamp load, max.	10 Hz
Total current of the outputs	
 Current per channel, max. 	0.5 A
Current per module, max.	2 A
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m
Analog inputs	
Number of analog inputs	16
permissible input current for current input (destruction limit), max.	30 mA
Input ranges	
Current	Yes; 0 10 mA, 0 20 mA, 4 20 mA, 4 20 mA HART
Input ranges (rated values), currents	
• 0 to 10 mA	Yes
— Input resistance (0 to 10 mA)	250 Ω
• 0 to 20 mA	Yes; 16 bit incl. sign
— Input resistance (0 to 20 mA)	250 Ω
• 4 mA to 20 mA	Yes; 16 bit incl. sign
— Input resistance (4 mA to 20 mA)	250 Ω
Analog value generation for the inputs	
Analog value generation for the inputs Measurement principle	integrating (Sigma-Delta)
	integrating (Sigma-Delta)
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max.	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception:
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Smoothing of measured values	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders • 2-wire sensor	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max.	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Smoothing of measured values parameterizable Encoder Connection of signal encoders for current measurement as 2-wire transducer Connectable encoders 2-wire sensor permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-)	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-)	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min.	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB
Measurement principle Integration and conversion time/resolution per channel • Resolution with overrange (bit including sign), max. • Integration time, parameterizable Smoothing of measured values • parameterizable Encoder Connection of signal encoders • for current measurement as 2-wire transducer Connectable encoders • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-)	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Smoothing of measured values parameterizable Encoder Connection of signal encoders for current measurement as 2-wire transducer Connectable encoders 2-wire sensor permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C)	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB 0.05 %
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Smoothing of measured values parameterizable Encoder Connection of signal encoders for current measurement as 2-wire transducer Connectable encoders 2-wire sensor permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) Current, relative to input range, (+/-)	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB 0.05 %
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Smoothing of measured values parameterizable Encoder Connection of signal encoders for current measurement as 2-wire transducer Connectable encoders 2-wire sensor permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C)	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB 0.05 %
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Smoothing of measured values parameterizable Encoder Connection of signal encoders for current measurement as 2-wire transducer Connectable encoders Permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) Current, relative to input range, (+/-) Interrupts/diagnostics/status information Diagnostics function	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB 0.05 %
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Smoothing of measured values parameterizable Encoder Connection of signal encoders for current measurement as 2-wire transducer Connectable encoders Permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) Current, relative to input range, (+/-) Interrupts/diagnostics/status information	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB 0.05 % 0.1 %
Measurement principle Integration and conversion time/resolution per channel Resolution with overrange (bit including sign), max. Integration time, parameterizable Smoothing of measured values parameterizable Encoder Connection of signal encoders for current measurement as 2-wire transducer Connectable encoders Permissible quiescent current (2-wire sensor), max. Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) Current, relative to input range, (+/-) Interrupts/diagnostics/status information Diagnostics function	16 bit; Resolution with overrange (bit including sign), max. 16 bits, exception: 15 bits at 60 Hz interference suppression and 0 to 10 mA Yes; channel by channel Yes; none, weak, medium, strong, channel-by-channel Yes Yes 1.5 mA 0.01 % 0.005 %/K 60 dB 0.05 % 0.1 % Yes

	V.
Maintenance interrupt	Yes
Limit value alarm	Yes; two upper and two lower limit values in each case
Hardware interrupt	Yes; Parameterizable, channels 0 to 15, rising/falling edge
Diagnoses	
 Monitoring the supply voltage 	Yes
Wire-break	Yes; channel by channel
Short-circuit to M	Yes; Encoder supply to M, channel by channel
Group error	Yes
Overflow/underflow	Yes; channel by channel
Diagnostics indication LED	
MAINT LED	Yes; Yellow LED
 Monitoring of the supply voltage (PWR-LED) 	Yes; green PWR LED
 Channel status display 	No
 for channel diagnostics 	No
 for module diagnostics 	Yes; green/red DIAG LED
Integrated Functions	
Frequency measurement	Yes
 Number of frequency meters 	8
Counting functions	
 Continuous counting 	Yes
Counter response parameterizable	Yes
Hardware gate via digital input	Yes; Via partner channel (digital input n+8)
Software gate	Yes
Measuring functions	
Dynamic measurement period adjustment	Yes
Measuring range	
— Frequency measurement, min.	0.1 Hz
Frequency measurement, max.	5 kHz
Accuracy	
Frequency measurement	100 ppm; depending on measuring interval and signal evaluation
Potential separation	
Potential separation channels	
between the channels	No
 between the channels and backplane bus 	Yes
Between the channels and load voltage L+	No
Isolation	
Isolation tested with	1 500 V DC/1 min, type test
Ambient conditions	, VI
Ambient temperature during operation	
horizontal installation, min.	-40 °C
horizontal installation, max.	70 °C; Observe derating
vertical installation, min.	-40 °C
vertical installation, max.	60 °C; Observe derating
Dimensions	
Width	22.5 mm
Height	115 mm
Depth	138 mm
Weights	100 mill
Weight, approx.	150 g
ττοιχιτι, αρριτολ.	100 g
	_

last modified: 11/2/2021 🖸