SIEMENS

Data sheet

6DL1131-6TH00-0PH1



SIMATIC ET 200SP HA, digital input module, DI 16XNAMUR HA, suitable for terminal block H1, M1, color code CC01, channel diagnostics

General information		
Product type designation	DI 16xNAMUR HA	
Firmware version	V1.0	
 FW update possible 	Yes	
Usable terminal block	TB type H1, M1 and N0	
Color code for module-specific color identification plate	CC01	
Product function		
● I&M data	Yes; I&M0 to I&M3	
Engineering with		
 STEP 7 TIA Portal configurable/integrated from version 	V16	
 STEP 7 configurable/integrated from version 	V5.6	
 PCS 7 configurable/integrated from version 	V9.0	
 PCS neo can be configured/integrated from version 	V3.0	
 PROFINET from GSD version/GSD revision 	GSDML V2.3	
Operating mode		
• DI	Yes	
Counter	No	
Redundancy		
 Redundancy capability 	Yes; With TB type M1	
Supply voltage		
Rated value (DC)	24 V	
permissible range, lower limit (DC)	19.2 V	
permissible range, upper limit (DC)	28.8 V	
Reverse polarity protection	Yes	
Input current		
Current consumption (rated value)	95 mA	
Current consumption, max.	115 mA	
Encoder supply		
Number of outputs	16	
Output voltage, min.	8.1 V	
Short-circuit protection	Yes	
Power		
Power available from the backplane bus	74 mW	
Power loss		
Power loss, typ.	2.4 W	
Address area		
Address space per module		
Address space per module, max.	2 byte; + 2 bytes for QI information	
Digital inputs		
Number of digital inputs	16; NAMUR	

Distribution of a second simple	V
Digital inputs, parameterizable	Yes
Pulse extension	Yes; 0.5 s, 1 s, 2 s
Time stamping	Yes
Time stamp (with precision of 1 ms)	No
Edge evaluation	Yes; rising edge, falling edge, edge change
Signal change flutter	Yes; 2 to 32 signal changes
Flutter observation window	Yes; 0.5 s, 1 s to 100 s in 1-s steps
Input voltage	
Rated value (DC)	8.2 V
Input current	
for 10 k switched contact	
— for signal "0"	0.35 to 1.2 mA
— for signal "1"	2.1 6.4 mA
for unswitched contact	
— for signal "0", max. (permissible quiescent current)	0.5 mA
— for signal "1"	typ. 8 mA
for NAMUR encoders	
— for signal "0", min.	0.35 mA
— for signal "0", max.	1.2 mA
— for signal "1", min.	2.1 mA
— for signal "1", max.	6.4 mA
Input delay (for rated value of input voltage)	
• tolerated changeover time for changeover contacts	300 ms
for NAMUR inputs	
— at "0" to "1", max.	17 ms
— at "1" to "0", max.	25 ms
Cable length	
• shielded, max.	600 m
• unshielded, max.	200 m
Encoder	
Connectable encoders	
NAMED an analysis of the state	Yes
 NAMUR encoder/changeover contact according to EN 60947 	
	Yes
60947	
 60947 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 	Yes
 60947 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 	Yes Yes
 60947 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor 	Yes Yes; Acc. to NAMUR
 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor permissible quiescent current (2-wire sensor), max. 	Yes Yes; Acc. to NAMUR
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max.	Yes Yes; Acc. to NAMUR
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms	Yes Yes; Acc. to NAMUR 1.2 mA
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm	Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt	Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses	Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable	Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage	Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable	Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable Monitoring of encoder power supply	Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes
 60947 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable Monitoring of encoder power supply Wire-break Short-circuit 	Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable Monitoring of encoder power supply Wire-break Short-circuit Group error	Yes Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ	Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable Monitoring of encoder power supply Wire-break Short-circuit Group error	Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable Monitoring of encoder power supply Wire-break Short-circuit Group error Changeover contact error Diagnostics indication LED MAINT LED 	Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage parameterizable Monitoring of encoder power supply Wire-break Short-circuit Group error Changeover contact error Diagnostics indication LED MAINT LED Monitoring of the supply voltage (PWR-LED) 	Yes Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable Monitoring of encoder power supply Wire-break Short-circuit Group error Changeover contact error Diagnostics indication LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display 	Yes Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable Monitoring of encoder power supply Wire-break Short-circuit Group error Changeover contact error Diagnostics indication LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics 	Yes Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms Diagnostic alarm Hardware interrupt Diagnoses Diagnostic information readable Monitoring the supply voltage — parameterizable Monitoring of encoder power supply Wire-break Short-circuit Group error Changeover contact error Diagnostics indication LED MAINT LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics 	Yes Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor	Yes Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
• Single contact / changeover contact unconnected • Single contact / changeover contact connected with 10 kΩ • 2-wire sensor — permissible quiescent current (2-wire sensor), max. Interrupts/diagnostics/status information Alarms • Diagnostic alarm • Hardware interrupt Diagnoses • Diagnostic information readable • Monitoring the supply voltage — parameterizable • Monitoring of encoder power supply • Wire-break • Short-circuit • Group error • Changeover contact error Diagnostics indication LED • MAINT LED • Monitoring of the supply voltage (PWR-LED) • Channel status display • for channel diagnostics • for module diagnostics • for module diagnostics Potential separation Potential separation channels	Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y
 Single contact / changeover contact unconnected Single contact / changeover contact connected with 10 kΩ 2-wire sensor	Yes Yes Yes; Acc. to NAMUR 1.2 mA Yes; channel by channel Yes; Parameterizable, channels 0 to 15, rising/falling edge Yes Yes Yes Yes Yes Yes Yes Yes Yes Y

 Between the channels and load voltage L+ 	Yes	
Isolation		
Isolation tested with	1 500 V DC/1 min, type test	
Ambient conditions		
Ambient temperature during operation		
 horizontal installation, min. 	-40 °C	
 horizontal installation, max. 	70 °C	
 vertical installation, min. 	-40 °C	
 vertical installation, max. 	60 °C	
Dimensions		
Width	22.5 mm	
Height	115 mm	
Depth	138 mm	
Weights		
Weight, approx.	153 g	

last modified: 11/2/2021 🖸