SIEMENS

Data sheet 6ES7655-5PX31-1XX0

SIMATIC Compact Field Unit, Consisting of: 1x SIMATIC CFU DIQ (6ES7655-5PX31-1XX0), 1x SIMATIC CFU push-in terminals (6ES7655-5PX00-1XX0), premounted and checked



General information	
Product type designation	DIQ Bundle
HW functional status	FS01
Firmware version	V1.2
FW update possible	Yes
Vendor identification (VendorID)	002AH
Device identifier (DeviceID)	060FH
Number of channels	16
Product function	
• I&M data	Yes; I&M0 to I&M4
• Isochronous mode	No
 The user can configure digital channels as input/output as required 	Yes
Digital channels can be parameterized	Yes
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V17
 STEP 7 configurable/integrated from version 	V5.6 HF2 and higher
 PCS 7 configurable/integrated from version 	V9.0 SP2 and higher
 PCS neo can be configured/integrated from version 	V3.1
 PROFIBUS from GSD version/GSD revision 	-1-
 PROFINET from GSD version/GSD revision 	GSDML V2.3
Operating mode	
Counter	Yes
Installation type/mounting	
Mounting	on 35 mm DIN rail, 2 spacing units wide
Mounting position	Horizontal, vertical
Supply voltage	
Type of supply voltage	24 V DC
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Short-circuit protection	Yes
Redundant power supply	Yes
Mains buffering	
 Mains/voltage failure stored energy time 	5 ms; For communication
Input current	
Current consumption (rated value)	5.12 A
Current consumption, max.	5.13 A
Inrush current, max.	4.8 A

I²t	0.073 A²-s
Encoder supply	
Number of outputs	16
Output voltage, min.	18.2 V
Short-circuit protection	Yes; Electronic
Output current	,
• up to 60 °C, max.	5 A
• up to 70 °C, max.	4 A
Power loss	
Power loss, typ.	2.88 W; Depending on the type of BusAdapter used (typ. RJ45)
Address area	E. E. C., Dopontaling on the type of Buor laupter according. Noted
Address space per station	
Address space per station, max.	1 440 byte; Dependent on configuration
Digital inputs	
Number of digital inputs	16
Source/sink input	Yes; P-reading
Input characteristic curve in accordance with IEC 61131, type 1	Yes
Input characteristic curve in accordance with IEC 61131, type 1	No
Input characteristic curve in accordance with IEC 61131, type 3	Yes
Pulse extension	No
Number of simultaneously controllable inputs	
horizontal installation	
— up to 60 °C, max.	16; Total current must be observed, see DQ
— up to 70 °C, max.	16; Total current must be observed, see DQ
vertical installation	
— up to 60 °C, max.	16; Total current must be observed, see DQ
Digital input functions, parameterizable	
• Counter	Yes
— Number, max.	2
— Counting frequency, max.	1 kHz
— Counting width	32 bit
Counting direction up/down	Yes; Up
Input voltage	
Rated value (DC)	24 V
• for signal "0"	-30 to +5 V
• for signal "1"	+11 to +30V
Input current	
• for signal "1", typ.	2.5 mA; Typical
Input delay (for rated value of input voltage)	
for standard inputs	
— parameterizable	No
— at "0" to "1", max.	3.2 ms; for counter function 0,1 ms
— at "1" to "0", max.	3.2 ms; for counter function 0,1 ms
Cable length	
• shielded, max.	1 000 m
unshielded, max.	600 m
Digital outputs	
Type of digital output	Transistor
Number of digital outputs	16
Current-sinking	No
Current-sourcing	Yes
Short-circuit protection	Yes
Response threshold, typ.	0.7 to 1.3 A
Limitation of inductive shutdown voltage to	Typ. L+ (-50 V)
Controlling a digital input	Yes
Switching capacity of the outputs	
● on lamp load, max.	5 W
Load resistance range	
• lower limit	48 Ω
• upper limit	12 kΩ

Output voltage	
Output voltage	DC
Type of output voltagefor signal "1", min.	Ue minus 1 V
Output current	Oe minus 1 V
• for signal "1" rated value	0.5 A
• for signal "0" residual current, max.	0.1 mA
Output delay with resistive load	V. I IIIA
• "0" to "1", max.	50 µs
• "1" to "0", max.	100 μs
Parallel switching of two outputs	100 pc
• for uprating	No
for redundant control of a load	No
Switching frequency	
with resistive load, max.	100 Hz
with inductive load, max.	2 Hz
• on lamp load, max.	10 Hz
Total current of the outputs	
Current per channel, max.	0.5 A
horizontal installation	
— up to 60 °C, max.	5 A
— up to 70 °C, max.	4 A
vertical installation	
— up to 60 °C, max.	5 A
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m
Encoder	
Connectable encoders	
• 2-wire sensor	Yes
— permissible quiescent current (2-wire sensor), max.	1.5 mA
Interfaces	
N I (DDOEINET); ;	
Number of PROFINET interfaces	1
Number of PROFIBUS interfaces Number of PROFIBUS interfaces	0
Number of PROFIBUS interfaces	0 PROFINET
Number of PROFIBUS interfaces 1. Interface	0
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types	PROFINET Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports	0 PROFINET
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch	PROFINET Yes 2 Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET)	PROFINET Yes 2
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols	PROFINET Yes 2 Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device	PROFINET Yes 2 Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave	PROFINET Yes 2 Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types	PROFINET Yes 2 Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet)	PROFINET Yes 2 Yes Yes No
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps	PROFINET Yes 2 Yes Yes Yes Yes No
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation	PROFINET Yes 2 Yes Yes Yes Yes No
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing	PROFINET Yes 2 Yes Yes Yes Yes No
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols	PROFINET Yes 2 Yes Yes No Yes Yes Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO	PROFINET Yes 2 Yes Yes Yes Yes No
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode	PROFINET Yes 2 Yes Yes Yes Yes No Yes Yes Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode • PROFINET system redundancy (S2)	PROFINET Yes 2 Yes Yes No Yes Yes Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode • PROFINET system redundancy (S2) Media redundancy	PROFINET Yes 2 Yes Yes Yes Yes No Yes Yes Yes Yes Yes Yes Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode • PROFINET system redundancy (S2) Media redundancy — MRP	PROFINET Yes 2 Yes Yes Yes Yes No Yes Yes Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode • PROFINET system redundancy (S2) Media redundancy — MRP Open IE communication	O PROFINET Yes 2 Yes Yes Yes Yes Yes No Yes Yes Yes Yes Yes Yes Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode • PROFINET system redundancy (S2) Media redundancy — MRP Open IE communication • LLDP	PROFINET Yes 2 Yes Yes Yes Yes No Yes Yes Yes Yes Yes Yes Yes Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode • PROFINET system redundancy (S2) Media redundancy — MRP Open IE communication • LLDP Interrupts/diagnostics/status information	PROFINET Yes 2 Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode • PROFINET system redundancy (S2) Media redundancy — MRP Open IE communication • LLDP Interrupts/diagnostics/status information Status indicator	PROFINET Yes 2 Yes
Number of PROFIBUS interfaces 1. Interface Interface type Isolated Interface types • Number of ports • integrated switch • BusAdapter (PROFINET) Protocols • PROFINET IO Device • PROFIBUS DP slave Interface types RJ 45 (Ethernet) • 100 Mbps • Autonegotiation • Autocrossing Protocols Supports protocol for PROFINET IO Redundancy mode • PROFINET system redundancy (S2) Media redundancy — MRP Open IE communication • LLDP Interrupts/diagnostics/status information	PROFINET Yes 2 Yes

Diagnoses Monitoring of encoder power supply Wire-break Short-circuit Yes Diagnostics indication LED RUN LED REROR LED REROR LED MAINT LED Maintring of the supply voltage (PWR-LED) Status indicator digital input (green) Status indicator digital output (green) Status indicator digital output (green) Status indicator digital output (green) Status indicator digital input (green) Status indicator digital input (green) Potential separation between the channels and PROFINET Potential separation digital inputs Setween the channels Setween the channels and the power supply of the electronics Potential separation digital outputs Setween the channels Setwe
Wire-break Short-circuit Yes Diagnostics indication LED RUN LED REROR LED Yes; green LED Yes; red LED MAINT LED Yes; red LED Monitoring of the supply voltage (PWR-LED) Status indicator digital input (green) Status indicator digital output (green) Status indicator digital output (green) Yes Potential separation between the channels and PROFINET Potential separation digital inputs between the channels between the channels and the power supply of the electronics Potential separation digital outputs between the channels
Short-circuit Piagnostics indication LED RUN LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Status indicator digital input (green) Status indicator digital output (green) Status indicator digital output (green) Status indicator digital input (green) Potential separation between the channels and PROFINET Potential separation digital inputs Detween the channels Detween the channels and the power supply of the electronics Potential separation digital outputs Detween the channels
Diagnostics indication LED RUN LED RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Status indicator digital input (green) Status indicator digital output (green) Status indicator digital output (green) Potential separation between the channels and PROFINET Potential separation digital inputs Detween the channels Detween the channels and the power supply of the electronics Potential separation digital outputs Detween the channels Detween the channels No Detween the channels Detween the channels No Detween the channels Detween the channels and the power supply of the electronics
RUN LED ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Status indicator digital input (green) Status indicator digital output (green) Status indicator digital output (green) Status indicator digital output (green) Potential separation between the channels and PROFINET Potential separation digital inputs between the channels between the channels and the power supply of the electronics Potential separation digital outputs between the channels No No between the channels No No between the channels and the power supply of the electronics
ERROR LED MAINT LED Monitoring of the supply voltage (PWR-LED) Status indicator digital input (green) Status indicator digital output (green) Status indicator digital output (green) Status indicator digital output (green) Potential separation between the channels and PROFINET Potential separation digital inputs between the channels between the channels
MAINT LED Monitoring of the supply voltage (PWR-LED) Status indicator digital input (green) Status indicator digital output (green) Status indicator digital output (green) Potential separation between the channels and PROFINET Potential separation digital inputs between the channels between the channels No between the channels and the power supply of the electronics Potential separation digital outputs between the channels between the channels No between the channels and the power supply of the electronics No
Monitoring of the supply voltage (PWR-LED) Status indicator digital input (green) Status indicator digital output (green) Status indicator digital output (green) Potential separation between the channels and PROFINET Potential separation digital inputs between the channels between the channels between the channels of the electronics Potential separation digital outputs between the channels between the channels of the electronics No
Status indicator digital input (green) Status indicator digital output (green) Yes Potential separation between the channels and PROFINET Yes Potential separation digital inputs • between the channels • between the channels and the power supply of the electronics Potential separation digital outputs • between the channels and the power supply of the electronics No • between the channels and the power supply of the electronics
Status indicator digital output (green) Potential separation between the channels and PROFINET Potential separation digital inputs • between the channels • between the channels and the power supply of the electronics Potential separation digital outputs • between the channels • between the channels and the power supply of the electronics No • between the channels and the power supply of the electronics
Potential separation between the channels and PROFINET Potential separation digital inputs • between the channels • between the channels and the power supply of the electronics Potential separation digital outputs • between the channels • between the channels • between the channels • between the channels and the power supply of the electronics
between the channels and PROFINET Potential separation digital inputs • between the channels • between the channels and the power supply of the electronics Potential separation digital outputs • between the channels • between the channels • between the channels and the power supply of the electronics
Potential separation digital inputs • between the channels • between the channels and the power supply of the electronics Potential separation digital outputs • between the channels • between the channels • between the channels and the power supply of the electronics
between the channels between the channels and the power supply of the electronics Potential separation digital outputs between the channels between the channels between the channels and the power supply of the electronics No
between the channels and the power supply of the electronics Potential separation digital outputs between the channels between the channels and the power supply of the electronics No No
electronics Potential separation digital outputs • between the channels • between the channels and the power supply of the electronics No
 between the channels between the channels and the power supply of the electronics No
between the channels and the power supply of the electronics
electronics
Isolation
- Solution
Isolation tested with 1 500 V AC between PROFINET and electronics
Degree and class of protection
IP degree of protection IP20
Ambient conditions
Ambient temperature during operation
• min40 °C
• max. 70 °C
• horizontal installation, min40 °C
 horizontal installation, max. 70 °C; Observe derating
• vertical installation, min40 °C
• vertical installation, max. 60 °C; Observe derating
Ambient temperature during storage/transportation
• min40 °C
• max. 70 °C
Relative humidity
• Operation, max. 95 %
connection method
Design of electrical connection Connection plug
Dimensions
Width 329 mm
Height 123 mm
Depth 74 mm
Weights
Weight, approx. 610 g

last modified: 9/2/2021