

Conrad WLAN Repeater N300 Item No. 986922

Firmware update, Version "RPTN2-B2W.GD.R3464.0.20161028"

This ZIP archive contains the firmware file

"WN518W2-B2_conrad_RPTN2-B2W.GD.R3464.0.20161028.NOhw_fw.c.bin"

and a manual for German and English. To upgrade the repeater you must upload the firmware file to the repeater. Please check before update that your repeater has not the new version.

- The update solve a problem while reset the device
- The synchronisation with time has been improved
- The translation for English and German has been adapted

Firmware installation:

1.

First unpack the archive with the firmware.

2.

If your device is configured at the moment please make first a reset to the factory default before update the firmware. Otherwise you can't access the web interface. For more details see the chapter 14 in the main manual.

3.

When the restart is done connect your computer with a LAN cable to the LAN port of the repeater. See also the chapter 7 in the main manual.

4.

Open the web interface. See chapter 9 in the main manual.

5.

In the web interface navigate to the point "**Management**" in the left menu and click on the point "**Upgrade Firmware**".

6.

Now click the button "**Choose File**" and take the firmware file **"WN518W2-B2_conrad_RPTN2-B2W.GD.R3464.0.20161028.NOhw_fw.c.bin"**.

7.

Click "**Upload**" to start the update.

→ This can take several minutes.

8.

If the update is done, check the version on the status site. (Click "**Professional Setup**"). The version behind "**Firmware Version**" should be "**RPTN2-2W.GD.R3464.0.20161028**" and the "**Build Time**" should be "**Fri Oct28 16:51:27 CST 2016**".

9.

Now you can setup the device. We recommend making a reset to the factory defaults before reconfigure the device. See the chapter 14 in the main manual.