

## LINE OUTPUT PENTODE

Beam pentode intended for use as line output tube in television receivers.

**HEATING:** Indirect by A.C. or D.C.; parallel supply

Heater voltage	$V_f$	6.3 V
Heater current	$I_f$	1.38 A

**LIMITING VALUES** (Design centre rating system)

Cathode to heater voltage,

DC + peak, k positive	$V_{kf}$	max. 200 V
k negative	$-V_{kf}$	200 V <sup>1)</sup>

-----  
 For further data and curves of this type  
 please refer to type PL 504  
 -----

<sup>1)</sup> DC component max. 100 V.

# PHILIPS

Data handbook



Electronic  
components  
and materials

**EL504**

**page**

1

2

**sheet**

1

FP

**date**

1969.01

1999.03.19