

# **PCB Power Relay**

G5NB-E

# A Miniature Relay with 1-pole 5 A Switching Capability and 10 kV Impulse Withstand Voltage

- Highly efficient magnetic circuit for high sensitivity (200 mW).
- Compact slim, yet provides 10 kV impulse withstand voltage (between coil and contacts).
- Standard model conforms to UL, CSA and VDE standards
- Tracking resistance: CTI>250
- Contains no lead inside and features cadmiumfree contacts ensuring environment-friendly use





### Ordering Information \_\_\_\_\_

Classification	Contact form	Enclosure ratings	Model
Standard	SPST-NO	Flux protection	G5NB-1A-E

**Note:** When ordering, add the rated coil voltage to the model nur Example: G5NB-1A-E 12 VDC

Rated coil voltage

**Model Number Legend** 

G5NB- $\square$   $\square$ -E  $\square$  VDC

1. Number of Poles

3. Rated Coil Voltage

1: 1 pole

5, 12, 18, 24 VDC

2. Contact Form
A: SPST-NO

## Application Examples -

Water heaters, refrigerators, air conditioners, and small electric appliances

# Coil Rating \_\_\_\_\_

Rated voltage	5 VDC	12 VDC	18 VDC	24 VDC
Rated current	40.0 mA	16.7 mA	11.1 mA	8.3 mA
Coil resistance	125 Ω	720 Ω	1,620 Ω	2,880 Ω
Must operate voltage	75% max. of rated voltage			
Must release voltage	10% min. of rated voltage			
Max. voltage	170% of rated voltage (at 23°C)			
Power consumption	Approx. 200 mW			

Note: The rated current and coil resistance are measured at a coil temperature of 23°C with a tolerance of ±10%.

The operating characteristics are measured at a coil temperature of 23°C.

The "Max. voltage" is the maximum voltage that can be applied to the relay coil.

# Contact Rating \_\_\_\_\_

Load	Resistive load (cos $\phi$ = 1)
Rated load	5 A at 250 VAC, 3 A at 30 VDC
Max. switching voltage	250 VAC, 30 VDC
Max. switching current	5 A
Max. switching power	1250 VA, 90 W
Failure rate (reference value)	10 mA at 5 VDC

**Note:** P level:  $\lambda_{60} = 0.1 \times 10^{-6}$  /operation (with an operating frequency of 120 operations/min)

## Characteristics \_\_\_\_\_

100 mΩ max.
10 ms max.
10 ms max.
1,000 M $\Omega$ min. (at 500 VDC)
4,000 VAC, 50/60 Hz for 1 min between coil and contacts 750 VAC, 50/60 Hz for 1 min between contacts of same polarity
10,000 V (1.2 x 50 ms) between coil and contacts
Destruction: 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude) Malfunction: 10 to 55 to 10 Hz, 0.75-mm single amplitude (1.5-mm double amplitude)
Destruction: 1,000 m/s <sup>2</sup> Malfunction: 100 m/s <sup>2</sup>
Mechanical: 5,000,000 operations min. Electrical: 100,000 operations min (5 A at 250 VAC), 100,000 operations min. (3 A at 30 VDC)
5 VDC, 10 mA
Operating: -40°C to 85°C (with no icing or condensation)
Operating: 5% to 85%
Approx. 4 g

Note: 1. The data shown above are initial value.

- 2. Measurement conditions: 5 VDC, 1 A, voltage drop method.
- 3. Measurement conditions: Measured at the same points as the dielectric strength using a 500-VDC ohmmeter.
- **4.** This value is for a switching frequency of 120 operations/minute.

### Approved Standards -

### **UL508** (File No. 41515)

Coil ratings	Contact ratings
5 to 24 VDC	5 A, 30 VDC (resistive)
	5 A, 250 VAC (general use)

#### CSA C22.2 (No. 0, No. 1, No. 14) (File No. LR31928)


Coil ratings	Contact ratings	
5 to 24 VDC	5 A, 30 VDC (resistive)	
	5 A, 250 VAC (general use)	

## Actual Load Life (Reference Values) -


- 1. 120-VAC motor and lamp load (2.5-A surge and 0.5-A normal): 250,000 operations min.(at 23°C)
- 2. 160-VDC valve load (with varistor) (0.24-A): 250,000 operations min.(at 23°C)

### **Engineering Data**


#### **Maximum Switching Capacity**




#### Endurance



#### **Ambient Temperature vs. Maximum Coil Voltage**



#### **Malfunctioning Shock**




Quantity Tested: 5 units
Test Method: Shock was applied 3

times in 6 directions along 3 axes and the level at which shock caused malfunction was measured.


Rating: 100 m/s<sup>2</sup>

### **Dimensions**

Note: All units are in millimeters unless otherwise indicated.



Terminal Arrangement/ Internal Connections (Bottom View)



(No coil polarity)

### Precautions -

#### **CORRECT USE**

#### Handling

The enclosure rating of the G5NB is for flux protection. Do not use immersion-cleaning.

ALL DIMENSIONS SHOWN ARE IN MILLIMETERS.

To convert millimeters into inches, multiply by 0.03937. To convert grams into ounces, multiply by 0.03527.

Cat. No. G5NB-E In the interest of product improvement, specifications are subject to change without notice.



### **Omron Electronic Components Europe BV**

Tel: +31 23 568 1200 Fax: +31 23 568 1212