HF116F-1

MINIATURE HIGH POWER RELAY



File No.:E134517



File No.:R50154722



File No.:CQC09002031231(DC type)



Features

COIL DATA

- 30A switching capability
- 4kV dielectric strength (between coil and contacts)
- 3mm contact gap available
- UL insulation system: Class F available
- Environmental friendly product (RoHS compliant)

at 23°C

Outline Dimensions: (50.5 x 33.5 x 48.0) mm

CONTACT DATA		
Contact arrangement	nt 1A	
Contact resistance	100mΩ max.(at 1A 24VDC)	
Contact material	AgSnO ₂ , AgCdO	
Contact rating (Res. load)	30A 240VAC	25A 240VAC
	30A 277VAC	25A 277VAC
Max. switching voltage	277VAC	
Max. switching current	30A	25A
Max. switching power	8310VA	6925VA
Mechanical endurance	1 x 10 ⁷ ops	
Electrical endurance	(See approval repo	1 x 10 ⁵ OPS

CHARACTERISTICS					
Insulation	Insulation resistance		sulation resistance		1000MΩ (at 500VDC)
Dielectric Between		coil & contacts	4000VAC 1min		
strength	Between open contacts		2000VAC 1min		
Operate time (at nomi. volt.)		mi. volt.)	30ms max.(DC type)		
Release time (at nomi. volt.)		mi. volt.)	30ms max.(DC type)		
Shock resistance		Functional	98m/s ²		
		Destructive	980m/s²		
Vibration resistance			10Hz to 55Hz 1.5mm DA		
Ambient temperature		Ambient temperature -55°C to 70			
Humidity		Humidity			
Termination			PCB, QC, Screw		
Unit weight			Approx. 120g		
Construction			Dust protected		

Notes: 1) The data shown above are initial values.

- 2) Please find coil temperature curve in the characteristic curves below.
- 3) UL insulation system: Class F, Class B.

COIL	
Coil power	DC type: Approx. 1.9W;
	AC type: Approx. 2.7VA

Nominal Voltage VDC	Pick-up Voltage VDC max.	Drop-out Voltage VDC min.	Max. Allowable Voltage VDC	Coil Resistance Ω
3	2.25	0.3	3.3	4.7 x (1±10%)
6	4.50	0.6	6.6	18.8 x (1±10%)
12	9.00	1.2	13.2	75 x (1±10%)
24	18.0	2.4	26.4	300 x (1±10%)
48	36.0	4.8	52.8	1200 x (1±10%)
100	75.0	10.0	110	5200 x (1±10%)
110	82.5	11.0	121	6300 x (1±10%)
200	150	20.0	220	21000 x (1±10%)

Nominal Voltage VAC	Pick-up Voltage VAC	Drop-out Voltage VAC	Max. Allowable Voltage VAC	Coil Resistance Ω
6	4.80	0.90	6.6	18.8 x (1±10%)
12	9.60	1.80	13.2	75 x (1±10%)
24	19.2	3.60	26.4	300 x (1±10%)
48	38.4	7.20	52.8	1200 x (1±10%)
120	96.0	18.0	132	5200 x (1±10%)
220	176	33.0	242	20800 x (1±10%)


SAFETY APPROVAL RATINGS				
UL/CUL	AgSnO2	30A 277VAC		
		1.5HP 120VAC 3HP 240VAC		
		10A 120VAC		
	AgCdO	30A 277VAC		
		1.5HP 120VAC 3HP 240VAC		
		10A 120VAC Tungsten		
		TV-10 120VAC		
TÜV		27A 240VAC COSØ =0.8		
		25A 240VAC COSØ =0.4		
		25A 240VAC COSØ =1		

Notes: Only some typical ratings are listed above. If more details are required, please contact us.




ISO9001, ISO/TS16949, ISO14001, OHSAS18001, IECQ QC 080000 CERTIFIED

2012 Rev. 1.01




Notes: 1) For the applications of motor load, capacitive load and high inrush current, AgSnO2 contact material is recommended. For the applications of resistive load or low inductive load, AgCdO contact material is recommened.

OUTLINE DIMENSIONS, WIRING DIAGRAM AND PC BOARD LAYOUT



Outline Dimensions




Remark: 1) In case of no tolerance shown in outline dimension: outline dimension \leq 1mm, tolerance should be \pm 0.2mm; outline dimension >1mm and \leq 5mm, tolerance should be \pm 0.3mm; outline dimension >5mm, tolerance should be \pm 0.4mm.

2) The tolerance without indicating for PCB layout is always ±0.1mm.


Wiring Diagram (Bottom view)

1 Form A




Coil Inner Circuit

DC operation coil









CHARACTERISTIC CURVES


MAXIMUM SWITCHING POWER



ENDURANCE CURVE



COIL TEMPERATURE RISE



Percentage Of Nominal Coil Voltage

Disclaimer

This datasheet is for the customers' reference. All the specifications are subject to change without notice.

We could not evaluate all the performance and all the parameters for every possible application. Thus the user should be in a right position to choose the suitable product for their own application. If there is any query, please contact Hongfa for the technical service. However, it is the user's responsibility to determine which product should be used only.

© Xiamen Hongfa Electroacoustic Co., Ltd. All rights of Hongfa are reserved.