### Autotransformer

### **JET 250**



## Advantages

Integrated short circuit and overload protection

Very high efficiency

Very good moisture protection and low noise thanks to XtraDenseFill resinencapsulation  $\begin{tabular}{ll} \begin{tabular}{ll} \begin{tabular}{l$ 

Carrying handle, mains connecting lead NEMA5-15 (USA) and socket for mobile use  $\,$ 

## **Applications**

Autotransformer for mobile use for the adjustment of the voltage in 110 Vac networks to 230 Vac equipment when no electrical isolation is required.

### Standards

Autotransformer to: VDE 0570 Part 2-13, DIN EN 61558-2-13, EN 61558-2-13, IEC 61558-2-13

## **Approvals**





# Autotransformer **JET 250**

	Туре	JET 250
Ĵ٢	Input	
1+	Rated input voltage	110 Vac
	Rated frequency	50 - 60 Hz
Electrical data	Output	
ö	Rated output voltage	230 Vac
g	Rated Power	250 VA
.은	No-load voltage (app. x factor)	1.04
덩	Efficiency	94 %
픮	Environment	
	Ambient temperature max.	40 °C
	Safety and protection	
	Туре	Resin encapsulated transformer
	Class of Insulation System	A
	Protection index	IP 22
	Safety class	1
	Short circuit strength	non-inherently short-circuit proof
	Order numbers	
	Order Number	JET 250

	Туре	JET 250
30	Input	
	Terminals Input	Connecting cable with NEMAS-15 plug (USA)
Mechanical data	Output	
	Terminals Output	Protective contact socket
	Measures and weights	
g	Weight	3.10 kg
an.		
ch		
Je		
Me		