

ER17505



International size reference: A

ELECTRICAL CHARACTERISTICS

(Typical values for cells stored for one year or less, at 25°C)

Nominal capacity

3.6Ah

(At 3.0 mA, +25°C, 2.0V cut off. The capacity restored by the cell varies according to current drain, temperature and cut off voltage.)

Nominal voltage

3.6V

130mA

Maximum recommended continuous current

(To get 50% of the nominal capacity at +25°C with 2.0V cut off. Higher currents possible, consult EVE.)

Pulse capability: Typically up to 180mA(180mA/0.1 second pulses, drained every 2 min at 25°C from undischarged cells with 10µA base current, yield voltage readings above 3. 0V. The readings may vary according to the pulse characteristics, the temperature, and the cell's previous history. Fitting cell with a capacitor may be recommended in severe conditions. Consult EVE.)

Storage

(Recommended)

30°C max

(For more severe condition consult EVE)

Operating temperature range

-55℃ / +85℃

(Operation at temperature different from ambient may lead to reduced capacity and lower voltage plateau readings.)

Typical weight

KEY FEATURES


- ✓ High and stable operating voltage
- ✓ High minimum voltage during pulsina
- ✓ Low self discharge rate (less than 1% after1 year of storage at +25°C)
- ✓ Stainless steel container
- ✓ Hermetic glass-to-metal sealing
- ✓ Non-flammable electrolyte
- ✓ Compliant with IEC 86-4 safety standard and EN 50020 intrinsic safety
- "Underwriters Laboratories (UL) Component Recognition (File Number MH28717)

MAIN APPLICATIONS


- Utility metering
- Alarms and security devices
- Memory back-up
- Tracking systems
- Automotive electronics
- ✓ Professional electronics ... etc.

26g

2. VOLTAGE VS. TEMPERATURE



1.DISCHARGE CHARACTERISTICS@+25°C



Ø 6.2mm Max.


AVAILABLE TERMINATIONS

Ø 17.5mm Max.


Suffix-/S Standard Suffix-/T Solder Tabs Flying Leads Suffix-/W View available terminations

3. CAPACITY VS. CURRENT

TEMPERATURE(°C)



4. STORAGE CHARACTERISTICS



WARNING:

Fire, explosion and severe burn hazard. Do not recharge, crush, disassemble, heat above 100℃, incinerate, or expose contents to water

Note: Any representations in this data sheet concerning performance are for informational purpose only and are not construed as warranties, either expressed or implied, of future performance.

EVE ENERGY CO., LTD.

Address.: EVE Industrial Park, XiKeng Industrial zone, Huihuan Town, Huizhou, Guangdong, China

Operator: (86-752)260 6966 Direct:(86-752)261 0582

Fax: (86-752)260 6033 P.C.516006

http://www.evebattery.com Email: sales@evebattery.com

Latest version can be downloaded from the EVE website