DATASHEET - T0-2-8900/I1/SVB



Main switch, T0, 20 A, surface mounting, 2 contact unit(s), 3 pole + N, Emergency switching off function, With red rotary handle and yellow locking ring, Lockable in the 0 (Off) position



Part no. T0-2-8900/I1/SVB

Catalog No. 207151

EL-Nummer (Norway)

0001417155

Delivery program

Delivery program			
Product range			Main switch maintenance switch Repair switch
Part group reference			ТО
Stop Function			Emergency switching off function
			With red rotary handle and yellow locking ring
Number of poles			3 pole + N
Locking facility			Lockable in the 0 (Off) position
Degree of Protection			IP65
			totally insulated
Design			surface mounting
Contact sequence			0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
Switching angle		0	90
Design number			8900
Function			ION O OFF
Motor rating AC-23A, 50 - 60 Hz			
400 V	P	kW	5.5
Rated uninterrupted current	I _u	Α	20
Note on rated uninterrupted current !u			Rated uninterrupted current I_{U} is specified for max. cross-section.
Number of contact units		contact unit(s)	2

Technical data

General		
Standards		IEC/EN 60947, VDE 0660, IEC/EN 60204 Switch-disconnector according to IEC/EN 60947-3
Climatic proofing		Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Ambient temperature		
Enclosed	°C	-25 - +40
Overvoltage category/pollution degree		III/3

Rated impulse withstand voltage	U _{imp}	V AC	6000
Mechanical shock resistance	- IIIIp	g	15
Mounting position		9	As required
Contacts			As required
Mechanical variables			
Number of poles			3 pole + N
Electrical characteristics			
Rated operational voltage	U _e	V AC	690
Rated uninterrupted current	l _u	Α	20
Note on rated uninterrupted current !u			Rated uninterrupted current I _u is specified for max. cross-section.
Load rating with intermittent operation, class 12			
AB 25 % DF		x I _e	2
AB 40 % DF		x I _e	1.6
AB 60 % DF		x I _e	1.3
Short-circuit rating		·	
Fuse		A gG/gL	20
Rated short-time withstand current (1 s current)	I _{cw}	A _{rms}	320
Note on rated short-time withstand current lcw	***		Current for a time of 1 second
Rated conditional short-circuit current	Iq	kA	6
Switching capacity	-4		
cos φ rated making capacity as per IEC 60947-3		Α	130
Rated breaking capacity cos φ to IEC 60947-3		Α	
230 V		Α	100
400/415 V		Α	110
500 V		Α	80
690 V		Α	60
Safe isolation to EN 61140			
between the contacts		V AC	440
Current heat loss per contact at I _e		W	0.6
Current heat loss per auxiliary circuit at I _e (AC-15/230 V)		CO	0.6
Lifespan, mechanical	Operations	x 10 ⁶	> 0.4
Maximum operating frequency	Operations/h		1200
AC			
AC-3			
Rating, motor load switch	P	kW	
220 V 230 V	Р	kW	3
230 V Star-delta	Р	kW	5.5
400 V 415 V	Р	kW	5.5
400 V Star-delta	P	kW	7.5
500 V	P	kW	5.5
500 V Star-delta	P	kW	7.5
690 V	P	kW	4
690 V Star-delta	P	kW	5.5
Rated operational current motor load switch			
230 V	l _e	Α	11.5
230 V star-delta	I _e	Α	20
400V 415 V	I _e	Α	11.5
400 V star-delta	I _e	Α	20
500 V	I _e	Α	9
500 V star-delta	I _e	Α	15.6
690 V	I _e	Α	4.9
690 V star-delta	I _e	Α	8.5
AC-23A			
Motor rating AC-23A, 50 - 60 Hz	P	kW	
-			

J			
Tightening torque		lb-in	NIS.5 8.83
Terminal capacity Terminal screw			M3.5
Rating data for approved types			
Notes			$\mathrm{B10_{d}}$ values as per EN ISO 13849-1, table C1
Fechnical safety parameters:			
Tightening torque for terminal screw		Nm	1
Terminal screw			X (0.75 - 2.5) M3.5
Flexible with ferrules to DIN 46228		mm ²	1 x (0.75 - 2.5) 2 x (0.75 - 2.5)
Solid or stranded		mm ²	1 x (1 - 2,5) 2 x (1 - 2,5)
Terminal capacities			
Control circuit reliability at 24 V DC, 10 mA	Fault probability	H _F	< 10 ⁻⁵ ,< 1 failure in 100,000 switching operations
Voltage per contact pair in series		V	32
Rated operational current	le	Α	10
DC-13, Control switches L/R = 50 ms			
Contacts		Quantity	5
Rated operational current	I _e	Α	5
240 V			
Contacts		Quantity	
Rated operational current	I _e	Α	5
120 V		Launtity	-
Contacts	-е	Quantity	
Rated operational current	l _e	A	10
Contacts 60 V		Quantity	2
Rated operational current	l _e	A	10
48 V		^	10
Contacts		Quantity	1
Rated operational current	I _e	Α	10
24 V			
DC-23A, motor load switch $L/R = 15 \text{ ms}$			
Contacts		Quantity	1
Rated operational current	I _e	Α	1
DC-21A	l _e	Α	
Voltage per contact pair in series		V	60
Rated operational current	I _e	Α	10
DC-1, Load-break switches L/R = 1 ms			
DC	C		
690 V	l _e	A	7.6
500 V	I _e	A	13.3
400 V 415 V	l _e	A	13.3
230 V	l _e	A	13.3
Rated operational current motor load switch	r	KVV	5.5
500 V 690 V	P P	kW kW	7.5 5.5
400 V 415 V	P	kW	5.5
230 V	Р	kW	3

Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	20
Heat dissipation per pole, current-dependent	P _{vid}	W	0.6
Equipment heat dissipation, current-dependent	P _{vid}	W	0

Heat dissipation capacity Operating ambient temperature min. Operating ambient temperature max. IEC/EN 61439 design verification 10.2 Strength of materials and parts 10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of tresistance of insulating materials to normal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections 10.8 Connections for external conductors Pdiss W 0 40 Weets the product standard's requirements. Meets the product standard's requirements. Meets the product standard's requirements. UV resistance only in connection with protective shield. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Some not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Some not apply, since the entire switchgear needs to be evaluated. Some not apply, since the entire switchgear needs to be evaluated. Some not apply, since the entire switchgear needs to be evaluated. Some not apply, since the entire switchgear needs to be evaluated. Some not apply, since the entire switchgear needs to be evaluated.	
Operating ambient temperature max. IEC/EN 61439 design verification 10.2 Strength of materials and parts 10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections **C** 40 **A** **Meets the product standard's requirements. Meets the product standard's requirements. UV resistance only in connection with protective shield. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections	
IEC/EN 61439 design verification 10.2 Strength of materials and parts 10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.2 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections Meets the product standard's requirements. Meets the product standard's requirements. UV resistance only in connection with protective shield. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Incorporation of switching devices and components 10.7 Internal electrical circuits and connections	
10.2 Strength of materials and parts 10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3.0 Egree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections Meets the product standard's requirements. Weets the product standard's requirements witchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Incorporation of switching devices and components Is the panel builder's responsibility.	
10.2.2 Corrosion resistance 10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.2 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections Meets the product standard's requirements. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated. Soes not apply, since the entire switchgear needs to be evaluated.	
10.2.3.1 Verification of thermal stability of enclosures 10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections Meets the product standard's requirements. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility.	
10.2.3.2 Verification of resistance of insulating materials to normal heat 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation UV resistance only in connection with protective shield. 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.6 Mechanical impact 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Is the panel builder's responsibility.	
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting 10.2.6 Mechanical impact 10.2.7 Inscriptions 10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility.	
and fire due to internal electric effects 10.2.4 Resistance to ultra-violet (UV) radiation 10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.6 Mechanical impact 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. 10.4 Clearances and creepage distances Meets the product standard's requirements. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. Does not apply, since the entire switchgear needs to be evaluated. In the panel builder's responsibility.	
10.2.5 Lifting Does not apply, since the entire switchgear needs to be evaluated. 10.2.6 Mechanical impact Does not apply, since the entire switchgear needs to be evaluated. 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility.	
10.2.6 Mechanical impact 10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated. 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility.	
10.2.7 Inscriptions Meets the product standard's requirements. 10.3 Degree of protection of ASSEMBLIES Does not apply, since the entire switchgear needs to be evaluated. Meets the product standard's requirements. Meets the product standard's requirements. Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility.	
10.3 Degree of protection of ASSEMBLIES 10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility.	
10.4 Clearances and creepage distances Meets the product standard's requirements. 10.5 Protection against electric shock Does not apply, since the entire switchgear needs to be evaluated. 10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility.	
10.5 Protection against electric shock 10.6 Incorporation of switching devices and components 10.7 Internal electrical circuits and connections Does not apply, since the entire switchgear needs to be evaluated. Is the panel builder's responsibility.	
10.6 Incorporation of switching devices and components Does not apply, since the entire switchgear needs to be evaluated. 10.7 Internal electrical circuits and connections Is the panel builder's responsibility.	
10.7 Internal electrical circuits and connections Is the panel builder's responsibility.	
10.8 Connections for external conductors Is the panel builder's responsibility.	
10.9 Insulation properties	
10.9.2 Power-frequency electric strength Is the panel builder's responsibility.	
10.9.3 Impulse withstand voltage Is the panel builder's responsibility.	
10.9.4 Testing of enclosures made of insulating material Is the panel builder's responsibility.	
10.10 Temperature rise The panel builder is responsible for the temperature rise calculation. Eat provide heat dissipation data for the devices.	n will
10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgea observed.	must be
10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgea observed.	must be
10.13 Mechanical function The device meets the requirements, provided the information in the instribution leaflet (IL) is observed.	ction

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Switch disconnector (EC000216)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Switch disconnector (ecl@ss10.0.1-27-37-14-03 [AKF060013])

p and dodd folly		
Version as main switch		Yes
Version as maintenance-/service switch		Yes
Version as safety switch		Yes
Version as emergency stop installation		Yes
Version as reversing switch		No
Number of switches		1
Max. rated operation voltage Ue AC	V	690
Rated operating voltage	V	690 - 690
Rated permanent current lu	Α	20
Rated permanent current at AC-23, 400 V	Α	13.3
Rated permanent current at AC-21, 400 V	Α	20
Rated operation power at AC-3, 400 V	kW	5.5
Rated short-time withstand current lcw	kA	0.32
Rated operation power at AC-23, 400 V	kW	5.5
Switching power at 400 V	kW	5.5
Conditioned rated short-circuit current Iq	kA	6
Number of poles		3
Number of auxiliary contacts as normally closed contact		0
Number of auxiliary contacts as normally open contact		1

Number of auxiliary contacts as change-over contact	0
Motor drive optional	No
Motor drive integrated	No
Voltage release optional	No
Device construction	Complete device in housing
Suitable for ground mounting	Yes
Suitable for front mounting 4-hole	No
Suitable for front mounting centre	No
Suitable for distribution board installation	No
Suitable for intermediate mounting	No
Colour control element	Red
Type of control element	Door coupling rotary drive
Interlockable	Yes
Type of electrical connection of main circuit	Screw connection
Degree of protection (IP), front side	IP65
Degree of protection (NEMA)	Other

Dimensions





