

NT-II User Guide,

NT-II

Bluetooth Headset with NFC

Thank you for purchasing NT-II.

Technical Specifications:

Bluetooth CLASS 2, V3.0 + EDR
Compatible with Bluetooth profiles:
HSP, HFP, A2DP, AVRCP
Effective range: 10 meters
Speaker impedance: 32 ohm
Signal to noise ratio: > 93 +/- 3db
Frequency response: 20Hz - 20kHz
Polymer-Li Battery: built-in, 320mAh
Input: DC: 5V/160mA
Charge time: approx. 3 hours
Operating time: up to 10 hours of music
playback, up to 11 hours of talk-time
Standby time: up to 360 hours

Charging the Headset:

1. Insert USB charging cable into a USB port that supports 5V power output (e.g. AC/DC USB adapter or PC USB port).
2. Connect charging cable to the Micro-USB charging part of the NT-II headset.
3. Charging is in process when red LED light glows.
4. Charging is complete when blue LED light glows.

Powering On/Off:

Power On - Press and hold the Multifunction Key for approx. 3 seconds. Release when blue LED light flashes.

Power Off - Press and hold the Multifunction Key for approx. 5 seconds. Release when red LED light flashes.

Pairing Headset with Bluetooth Devices:

Enter Pairing Mode - Make sure the NT-II headset is powered off. Press and hold the Multifunctioning Key for approx. 6 seconds, release when red and blue LED lights flash alternately.

Pairing Headset with Bluetooth Mobile Phone:

Make sure the Bluetooth function on your phone has been enabled. Keep the NT-II headset and phone within a 1 meter range when pairing.

1. Enter pairing mode on the NT-II headset (red and blue LED lights flashing alternately).
 2. Search for new Bluetooth devices on your phone, after searching select 'MINIX NT-2'.
 3. According to the indication, enter password or PIN No. '0000', and the press 'Yes'/'Confirm' (depending on your Bluetooth device settings).
 4. After successfully pairing, select 'MINIX NT-2' in the Bluetooth device list, and press 'connect'.
 5. After successfully connecting, the blue LED light on the NT-II will continue to flash.
- NT-II headset will automatically connect to last connected device when powered on.

Pairing Headset with NFC Technology:

Make sure the NFC function has been enabled on your device, and simply tap your NFC enabled device to the assigned NFC location on the NT-II headset. A pairing message will appear on the screen of your device, press 'Yes' to complete pairing. Tap the NFC mark again to disconnect device.

Care & Maintenance:

Make sure to keep the headset dry at all times, and away from water. NT-II headset is not waterproof, contact with water will cause permanent damage to the internals of the headset.

Do not leave the headset in direct sunlight or places of extreme temperatures. Doing so will shorten the lifespan of the headset, causing damage to the internal battery and plastic casing.

Do not attempt to dismantle the headset. Any attempts to modify, alter or repair the headset will void the warranty.

Do not drop from excessive heights, doing so will result in permanent damage to the headset.

Do not use intensive chemicals or detergents to clean the headset.

Do not scrap the surface of the headset with sharp objects to avoid causing permanent damage to the plastic casing.



<http://www.facebook.com/minixtech>

Join the MINIX Forum at www.minixforum.com