



## SMART PLUG

HS100 / HS110\*

\*Smart Plug with Energy Monitoring.



### 1 Download TP-LINK Kasa app



OR



### 2 Connect mobile device to your Wi-Fi network



OR



*Note: The Smart Plug can only connect to 2.4GHz network.*

### 3 Launch Kasa and follow the app instructions




Quick Setup




Enjoy

#### Button



Press and hold until the Wi-Fi  LED blinks amber and green alternately (about 5 seconds) to initiate the App-Config process.

Press and hold until the Wi-Fi  LED blinks amber quickly (about 10 seconds) to reset the Smart Plug to factory defaults.

## LEDs



### Wi-Fi

**Blinking Amber and Green:** App-Config mode initiated.

**Quick Blinking Green:** Connecting to the network.

**Solid Green:** Connected to the network.

**Quick Blinking Amber:** Factory reset.

**Solid Amber:** Rebooting.

**Solid Red:** No network connection.

### Power

**Solid Green:** The Smart Plug is switched on.

**Off:** The Smart Plug is switched off.

## Frequently Asked Questions (FAQs)

### 1. What devices can I control with the Smart Plug?

You can control lights, fans, humidifiers, portable heaters, and any small appliances in accordance with the Smart Plug's specifications.

### 2. What should I do when I can't turn devices on or off?

Make sure that the devices connected to the Smart Plug are turned on, and that the Smart Plug is connected to the network.

### 3. What should I do when the Wi-Fi LED is lit solid red?

A solid red indicates no network connection, or that the App-Config process has failed. You can:

- Check for interference or relocate the Smart Plug to another location within the signal range.
- Make sure that you connect the Smart Plug to the 2.4GHz network.
- Repeat the App-Config process.
- Factory reset the Smart Plug and try to add it again.

## Technical Support



For technical support, advanced features, and usage tips for the Smart Plug, visit [www.tp-link.com](http://www.tp-link.com).