

Starter Set Security

Product ref.: 143398A0



Product features

- Starter set for reliable monitoring and increased security in your own four walls
- The Access Point connects the smartphone via the Homematic IP cloud with all Homematic IP devices
- The motion detector triggers an alarm if movements are detected within a distance of up to 12 m and a detection angle of 105 ° (approx.)
- The window / door contact triggers an alarm if a window or door is opened
- Comfortable control via the Homematic IP app
- Highly reliable HmIP radio protocol based on 868 MHz
- High security thanks to comprehensive AES encryption and server location in Germany - requires no personal data

Technical specifications

Access Point:

Supply voltage	Power supply unit (5 V)
Dimensions (W x H x D)	118 x 104 x 26 mm
Typ. open area RF range	400 m

Motion detector:

Supply voltage	2x 1.5 V LR6/mignon/AA
Battery life	3 years (typ.)
Dimensions (W x H x D)	52 x 65 x 34 mm
Typ. open area RF range	280 m

Window / Door Contact:

Supply voltage	1x 1.5 V LR03/micro/AAA
Battery life	2 years (typ.)
Dimensions (W x H x D)	102 x 15 x 20 mm
Typ. open area RF range	300 m

Logistical data

Product reference	143398A0
EAN code	4047976433988
Short description	HmIP-SK2
Packing unit	6
Packing dimensions	325 x 159 x 106 mm

Package contents

Home Control Access Point (plug-in mains adapter, network cable)

Motion detector- indoor (stand, wall mounting bracket)

Window / Door Contact - optical (caps in white and brown)

Batteries

Mounting accessories

User manuals