




Mono subwoofer output with integrated active crossover



3 microphone input channels with front combo connector



One-knob compressor and auto talkover per microphone channel

NEW

OMNITRONIC CM-5300 Club-Mixer

Professional 5-channel club mixer

- 5 stereo input channels with 3-band kill EQ
- 3 microphone input channels with front combo connector
- One-knob compressor and auto talkover per microphone channel
- Smooth dual-rail channel input faders (60 mm/100 mm)
- Rear stereo input FOH for stage mixers
- 2 balanced XLR main outputs
- Additional mono zone output with switchable 80Hz HPF
- Mono subwoofer output with integrated active crossover
- Adjustable effects send/return path for external effect units
- Rack installation, 7 U

No. 10006950

Technical specifications:

Power supply:	115/230 V AC, 50/60 Hz
Power consumption:	25 W
Inputs:	
MIC 1-3:	combination XLR/6.3 mm jack bal.
LINE 1-5:	RCA L/R
PHONO 1,2:	RCA L/R
AUX:	3.5 mm stereo jack
FOH:	6.3 mm jack bal.
FX SEND:	6.3 mm jack unbal.
Ausgänge:	
MAIN 1,2:	XLR L/R bal., RCA L/R
ZONE:	XLR bal.
SUB:	XLR bal.
REC:	RCA L/R
FX SEND:	6.3 mm jack unbal.
PHONES:	6.3 mm jack unbal.
Frequency range:	20-20 000 kHz
Distortion:	0.05 % (line)
S/N ratio:	>82 dB (line)
Dimensions (LxWxH):	383 x 483 x 106 mm (19", 7 U)
Weight:	4.7 kg