

VOLTCRAFT®

VOLTCRAFT® - TOP PERFORMANCE IN EVERY WAY

"Since 1982, our product range has been dynamically adapting to the constant changes in the industry. We commit to offering first-class quality to our customers while delivering an excellent cost-performance ratio. This philosophy remains the cornerstone of Voltcraft's success."

SPAS-8000 USB-CHARGING STATION



Nº 1544029

The network-powered charging station allows the connection of up to 8 USB consumers, e.g., Mobile telephones, smartphones, tablet computers or the like. All USB-A outputs can be connected with a max. of 2.4 A. The total output current is 8.4 A. The high-current outputs can be used for rapid-charging devices, e.g., IPad®, etc. can be used simultaneously. The numerous safety mechanisms ensure a reliable and safe charging operation.

FEATURES:

8 USB-A outputs // 42 W Power // Intelligent device detection for charge optimisation //

EQUIPMENT:

Auto-Detect device detection for optimum charging control $\!\!/\!\!/$ Overload protection $\!\!/\!\!/$ Short-circuit-protection $\!\!/\!\!/$

TECHNICAL DATA:

Number of outputs	8 x USB-Socket Type A
Output voltage	5 V/DC
Output current max. per channel	2.4 A
Output current (max.)	8.4 A
Power	42 W
Inputs	Euro-plug
Input voltage range	100 - 240 V/AC
Product dimensions (L x B x H)	98 x 71 x 34 mm
Weight	305 g



Charging station // Euro mains cable // Operating instructions //



This data sheet is a publication by Conrad Electronic SE, Klaus-Conrad-Str. 1, D-92240 Hirschau (www.conrad.com). All rights including translation reserved. Reproduction by any method, e.g. photocopy, microfilming, or the capture in electronic data processing systems require the prior written approval by the editor. Reprinting, also in part, is prohibited. This publication represent the technical status at the time of printing.