
Programming Quick Guide -LS6300J

Installation

Make sure that the scanner has the correct cable to plug into PC as below described,

After you plug cable into PC and hear the beep sound, the scanner can read the barcodes now.



Reset Configuration to Default:

(For USB HID)

If you are unsure of the scanner configuration or have scanned the incorrect codes, please scan the following barcode. This will reset the scanner to its factory defaults.



Keyboard Country (FOR USB HID Only)

Scan the appropriate country code as below to program the keyboard layout for your country or language. As a general rule, the following characters are supported, but need special care for countries other







Portuguese (Brazil)



Polish (Programmers)

Czech (QWERTZ)









Polish (214)

Dutch (Netherlands)

Ending character Setting



Cancel ending character



1D Symbologies - 1

CODABAR





CODE 39

ISSN

GS1 DataBar

GS1 Databar

Limited



Interleaved 25



























GS1 Databar **Expanded**



1D Symbologies - 2

Matrix 25 **ENABLE DISABLE CODE 93 CODE 128** GS1-128 UPC-A **UPC-E** EAN 8 **EAN 13 ISBN**

2D Symbologies

PDF 417









Micro QR Code



Data Matrix






Aztec Code



How to take out the USB cable

- Please insert a thin object (e.g. a bent paper clip) into the release hole.
- 2. Then, pull out the USB cable



Information in this document is subject to change without notice.
Q180515_01