

Instrument Security Procedures

Model: Fluke 1523/1524

Product Name: Reference Thermometer

Instrument Description: Handheld thermometer readout

Memory Description: The product contains non-volatile memory for recording temperature measurements. Temperature measurement data can be easily cleared. Non-volatile memory is also used for storing user settings and calibration correction coefficients. Settings cannot be erased but may be altered if necessary.

Memory Clearing Instructions:

To clear stored measurement data, follow these steps:

1. Push the **RECALL** button.
2. Push the **NEXT** button two times to select “Delete Saved”. Push **ENTER**.
3. The display indicates “SAVED: ALL”, “ENTER to Delete”. Push the **ENTER** button.
4. The display indicates, “Confirm DELETION”, “ENTER to Delete”. Push the **ENTER** button. The display indicates, “SAVED Empty”.

For Model 1524, continue with these steps:

5. Push the **RECALL** button.
6. Push the **NEXT** button four times to select “Delete Logs”. Push **ENTER**.
7. The display indicates “Tag: ALL”, “ENTER to Delete”. Push the **ENTER** button.
8. The display indicates, “Confirm DELETION”, “ENTER to Delete”. Push the **ENTER** button. The display indicates, “0 records”.