DATASHEET - T0-3-8297/I1



Changeoverswitches, T0, 20 A, surface mounting, 3 contact unit(s), Contacts: 6, 45 $^{\circ}$, momentary, Without 0 (Off) position, With spring-return to 1, 1<2, design no. 8297



Part no. T0-3-8297/l1 Catalog No. 222666

Similar to illustration

Delivery program			
Product range			Control switches
Part group reference			ТО
Basic function			Changeoverswitches
			with black thumb grip and front plate
Contacts			6
Degree of Protection			IP65
			totally insulated
Design			surface mounting
Contact sequence			1 2 1 0 2 0 3 0 4 0 X 5 0 6 0 7 0 8 0 10 0 11 0 12 0 X
Switching angle		o	45
Switching performance			momentary Without 0 (Off) position With spring-return to 1
Design number			8297
Front plate no.			FS 496
front plate			1<2
Motor rating AC-23A, 50 - 60 Hz			
400 V	P	kW	5.5

Rated uninterrupted current	I _u	Α	20
Note on rated uninterrupted current !u			Rated uninterrupted current $\mathbf{I}_{\mathbf{u}}$ is specified for max. cross-section.
Number of contact units		contact unit(s)	3

Technical data

General

Standards			IEC/EN 60947, VDE 0660, IEC/EN 60204 Switch-disconnector according to IEC/EN 60947-3
Climatic proofing			Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Ambient temperature			
Enclosed		°C	-25 - +40
Overvoltage category/pollution degree			III/3
Rated impulse withstand voltage	U _{imp}	V AC	6000
Mechanical shock resistance		g	15
Mounting position			As required
Contacts			
Electrical characteristics			
Rated operational voltage	U _e	V AC	690
Rated uninterrupted current	l _u	Α	20
Note on rated uninterrupted current !u			Rated uninterrupted current $I_{\rm u}$ is specified for max. cross-section.
Load rating with intermittent operation, class 12			
AB 25 % DF		x I _e	2
AB 40 % DF		x l _e	1.6
AB 60 % DF		x l _e	1.3
Short-circuit rating			
Fuse		A gG/gL	20
Rated short-time withstand current (1 s current)	I _{cw}	A _{rms}	320
Note on rated short-time withstand current lcw	·cw	rins	Current for a time of 1 second
Rated conditional short-circuit current		LΛ	6
Switching capacity	Iq	kA	
cos φ rated making capacity as per IEC 60947-3		Α	130
Rated breaking capacity cos φ to IEC 60947-3		Α	
230 V		Α	100
400/415 V		Α	110
500 V		Α	80
690 V		Α	60
Safe isolation to EN 61140			
between the contacts		V AC	440
Current heat loss per contact at I _e		W	0.6
Current heat loss per auxiliary circuit at I _e (AC-15/230 V)		CO	0.6
Lifespan, mechanical	Operations		> 0.4
		x 10 ⁶	
Maximum operating frequency	Operations/h		1200
AC			
AC-3	_		
Rating, motor load switch	Р	kW	
220 V 230 V	Р	kW	3
230 V Star-delta	P	kW	5.5
400 V 415 V	P	kW	5.5
400 V Star-delta	P	kW	7.5
500 V	P	kW	5.5
500 V Star-delta	Р	kW	7.5
690 V	Р	kW	4
690 V Star-delta	Р	kW	5.5
Rated operational current motor load switch			

239				
MOUNTS V				
		le	А	
SOU V star-delta		l _e		
SOV value debta	400 V star-delta	l _e	Α	20
680 V star-defta	500 V	l _e	Α	9
Band	500 V star-delta	le	Α	15.6
AC-22A Motor rating AC-23A, 50 - 60 Hz 230 V P NW 55 500 V P NW 55 880 V P P NW 55 880	690 V	l _e	Α	4.9
Motor rating AC 22A, 50 - 60 Hz	690 V star-delta	l _e	Α	8.5
200 V S S S S S S S S S	AC-23A			
## A0V 415 V P KW 5.5 500 V P KW 7.5 680 V P KW 5.5 Rated operational current motor load switch 230 V I Rated operational current motor load switch 3.3 400 V 415 V I Rated operational current Motor load switch 3.3 680 V Rated operational current Motor load switch 3.3 680 V Rated operational current 4.5 A 10	Motor rating AC-23A, 50 - 60 Hz	P	kW	
SOU	230 V	P	kW	3
Rated operational current motor load switch P	400 V 415 V	Р	kW	5.5
Rated operational current motor load switch I	500 V	Р	kW	7.5
A 13.3 400 V 415 V I I A 13.3 500 V I I A 13.3 690 V I I A 7.5 DC-I. Load-break switches L/R = 1 ms Rated operational current I A 10 Voltage per contact pair in series V 60 DC-21A I A 1 Contacts Quantity 1 Contacts Quantity 1 Contacts Quantity 1 Contacts Quantity 1 Rated operational current I A 10 Contacts Quantity 1 Rated operational current I A 10 Contacts Quantity 1 Rated operational current I A 10 Contacts Quantity 1 Rated operational current I A 10 Contacts Quantity 1 Rated operational current I A 10 Contacts Quantity 2 Rated operational current I A 10 Contacts Quantity 3 120 V Rated operational current I A 5 Contacts Quantity 3 Rated operational current I A 5 Contacts Quantity 3 Rated operational current I A 5 Contacts Quantity 3 Rated operational current I A 5 Contacts Quantity 3 Rated operational current I A 5 Contacts Quantity 6 Contacts Quantity 7 Contacts Quantity 7 Contacts Quantity 7 Contacts Quantity 7 Contacts Quantit	690 V	Р	kW	5.5
A				
Soul Incomposition Incom	230 V	l _e	Α	
Best	400 V 415 V	l _e	Α	13.3
DC	500 V	l _e	Α	13.3
DC-1, Load-break switches L/R = 1 ms	690 V	I _e	Α	7.6
Rated operational current	DC			
Voltage per contact pair in series DC-21A Rated operational current Contacts DC-23A, motor load switch L/R = 15 ms 24 V Rated operational current Contacts Rated operational current Rated operational cu	DC-1, Load-break switches L/R = 1 ms			
DC-21A	Rated operational current	l _e	Α	10
Rated operational current	Voltage per contact pair in series		V	60
Contacts	DC-21A	l _e	Α	
DC-23A, motor load switch L/R = 15 ms	Rated operational current	l _e	Α	1
Rated operational current Ie	Contacts		Quantity	1
Rated operational current 48 V Rated operational current Ie A 10 Contacts Quantity 1 48 V Rated operational current Ie A 10 Contacts Quantity 2 60 V Rated operational current Ie A 10 Contacts Quantity 3 120 V Rated operational current Ie A 5 Contacts Quantity 3 240 V Rated operational current Ie A 5 Contacts Quantity 3 Contacts Quantity 3	DC-23A, motor load switch L/R = 15 ms			
Contacts	24 V			
## Rated operational current Contacts	Rated operational current	l _e	Α	10
Rated operational current Contacts Quantity Rated operational current Ie A 10 Contacts Quantity 3 120 V Rated operational current Ie A 5 Contacts Quantity 3 240 V Rated operational current Ie A 5 Contacts Quantity 3 Contacts Quantity 5 DC-13, Control switches L/R = 50 ms	Contacts		Quantity	1
Contacts Quantity Rated operational current Contacts Quantity Rated operational current Ie A 5 Contacts Quantity A 5 Contacts Quantity Rated operational current Ie A 5 Contacts Quantity A 5 Contacts Quantity Rated operational current Ie A 5 Contacts Quantity Rated operational current Ie A 5 Contacts Quantity Rated operational current Ie A 5 Contacts Quantity DC-13, Control switches L/R = 50 ms				
Rated operational current Pe		l _e		
Rated operational current Contacts Quantity 120 V Rated operational current Ie A 5 Contacts Quantity 3 240 V Rated operational current Ie A 5 Contacts Quantity A 5 Quantity 5 DC-13, Control switches L/R = 50 ms			Quantity	2
Contacts 120 V Rated operational current Contacts Contacts Rated operational current Contacts Contacts Cuantity DC-13, Control switches L/R = 50 ms				
120 V Rated operational current Ie A 5 Contacts Quantity Rated operational current Ie A 5 Contacts Quantity Rated operational current Quantity Contacts Quantity DC-13, Control switches L/R = 50 ms	Rated operational current	l _e		
Rated operational current Contacts Quantity Rated operational current Rated operational current Rated operational current Contacts Quantity DC-13, Control switches L/R = 50 ms			Quantity	3
Contacts Quantity 240 V Rated operational current I _e A 5 Contacts Quantity 5 DC-13, Control switches L/R = 50 ms				
240 V Rated operational current Ie A 5 Contacts Quantity DC-13, Control switches L/R = 50 ms	Rated operational current	l _e		
Rated operational current I e A 5 Contacts DC-13, Control switches L/R = 50 ms J e A 5 Quantity 5			Quantity	3
Contacts Quantity DC-13, Control switches L/R = 50 ms				
DC-13, Control switches L/R = 50 ms		le		
			Quantity	5
nated operational current I _e A 10				10
		l _e		
Voltage per contact pair in series V 32		F 1:		
Control circuit reliability at 24 V DC, 10 mA Fault probability 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5 5	Control circuit reliability at 24 V DC, 10 mA		HF	< 10 ⁻⁵ ,< 1 failure in 100,000 switching operations
Terminal capacities				
Solid or stranded $mm^2 \qquad 1 \times (1 - 2,5) \\ 2 \times (1 - 2,5)$	Solid or stranded		mm ²	1 x (1 - 2,5) 2 x (1 - 2,5)
	Flexible with ferrules to DIN 46228		2	
Flexible with ferrules to DIN 46228 mm ² 1 x (0.75 - 2.5) 2 x (0.75 - 2.5)	THE TOTAL OF THE T		mm ⁻	2 x (0.75 - 2.5)
Terminal screw M3.5	Terminal screw			M3.5
Tightening torque for terminal screw Nm 1	Tightening torque for terminal screw		Nm	1

Technical safety parameters:

Notes	B10 _d values as per EN ISO 13849-1, table C1
Rating data for approved types	
Terminal capacity	
Terminal screw	M3.5

Design verification as per IEC/EN 61439

Design Verification as per IEC/EN 61439			
Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	20
Heat dissipation per pole, current-dependent	P _{vid}	W	0.6
Equipment heat dissipation, current-dependent	P _{vid}	W	0
Static heat dissipation, non-current-dependent	P _{vs}	W	0
Heat dissipation capacity	P _{diss}	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	40
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
$10.2.3.3\ Verification\ of\ resistance\ of\ insulating\ materials\ to\ abnormal\ heat\ and\ fire\ due\ to\ internal\ electric\ effects$			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			UV resistance only in connection with protective shield.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Control switch (EC002611)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Control switch (ecl@ss10.0.1-27-37-14-14 [ACN998011])

[ACN998011])		
Type of switch		Reverser
Number of poles		3
Max. rated operation voltage Ue AC	V	690
Rated permanent current lu	А	20
Number of switch positions		2
With 0 (off) position		No
With retraction in 0-position		No
Device construction		Surface mounted device
Width in number of modular spacings		0

Suitable for ground mounting	Yes
Suitable for front mounting 4-hole	No
Suitable for distribution board installation	No
Suitable for intermediate mounting	No
Complete device in housing	Yes
Type of control element	Toggle
Front shield size	48x48 mm
Degree of protection (IP), front side	IP65
Degree of protection (NEMA), front side	Other

Dimensions



