DATASHEET - T0-4-15374/IVS



Changeoverswitches, T0, 20 A, service distribution board mounting, 4 contact unit(s), Contacts: 8, 45 °, momentary, With 0 (Off) position, with spring-return from both directions to 0, 2 > 0 < 1, Design no. 15374



Similar to illustration

Part no. T0-4-15374/IVS Catalog No. 013716

D. P			
Delivery program			
Product range			Control switches
Part group reference			T0
Basic function			Changeoverswitches
			with black thumb grip and front plate
Contacts			8
Degree of Protection			Front IP30
Design			service distribution board mounting
Contact sequence			2 0 1 1 0 2 0 3 0 4 0 5 0 6 0 7 0 8 0 9 0 10 0 11 0 12 0 13 0 14 0 15 0 16 0 X
Switching angle		o	45
Switching performance			momentary With 0 (Off) position with spring-return from both directions to 0
Design number			15374
Front plate no.			FS 458
front plate			2>0<1
Motor rating AC-23A, 50 - 60 Hz			
400 V	P	kW	5.5
Rated uninterrupted current	I _u	А	20
Note on rated uninterrupted current !u			Rated uninterrupted current I _u is specified for max. cross-section.

Number of contact units	contact 4 unit(s)
	unit(s)

Technical data

General

General			150/5N 000/5 VDF 0000 J50/5N 000 VV
Standards			IEC/EN 60947, VDE 0660, IEC/EN 60204, CSA, UL Switch-disconnector according to IEC/EN 60947-3
Climatic proofing			Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Ambient temperature			
Open		°C	-25 - +50
Enclosed		°C	-25 - +40
Overvoltage category/pollution degree			III/3
Rated impulse withstand voltage	U _{imp}	V AC	6000
Mechanical shock resistance		g	15
Mounting position			As required
Contacts			
Electrical characteristics			
Rated operational voltage	U _e	V AC	690
Rated uninterrupted current	Iu	Α	20
Note on rated uninterrupted current !u			Rated uninterrupted current I _u is specified for max. cross-section.
Load rating with intermittent operation, class 12			
AB 25 % DF		x l _e	2
AB 40 % DF			1.6
		x l _e	
AB 60 % DF		x l _e	1.3
Short-circuit rating			
Fuse		A gG/gL	
Rated short-time withstand current (1 s current)	I _{cw}	A _{rms}	320
Note on rated short-time withstand current lcw			Current for a time of 1 second
Rated conditional short-circuit current	Iq	kA	6
Switching capacity			
cos φ rated making capacity as per IEC 60947-3		A	130
Rated breaking capacity cos φ to IEC 60947-3		A	
230 V		A	100
400/415 V		Α .	110
500 V		A	80
690 V		Α	60
Safe isolation to EN 61140			
between the contacts		V AC	440
Current heat loss per contact at I _e		W	0.6
Current heat loss per auxiliary circuit at I _e (AC-15/230 V)		CO	0.6
Lifespan, mechanical	Operations	x 10 ⁶	> 0.4
Maximum operating frequency	Operations/h		1200
AC			
AC-3			
Rating, motor load switch	P	kW	
220 V 230 V	P	kW	3
230 V Star-delta	P	kW	5.5
400 V 415 V	P	kW	5.5
400 V Star-delta	P	kW	7.5
500 V	P	kW	5.5
500 V Star-delta	P	kW	7.5
690 V	Р	kW	4
690 V Star-delta	Р	kW	5.5
Rated operational current motor load switch			
230 V	I _e	Α	11.5

MOV 15 V 15				
March Marc	230 V star-delta	l _e	Α	20
S00 V ran delta	400V 415 V	l _e	Α	11.5
S00 by star-detas	400 V star-delta	l _e	Α	20
GSD V	500 V	l _e	Α	9
	500 V star-delta	l _e	Α	15.6
Motor rating AC 22A, 50 + 60 10	690 V	le	Α	4.9
Metor rating AC 234, 90 - 90 hz P MV 220 V P MV 3 5 5 5 5 5 5 5 5 5	690 V star-delta	l _e	Α	8.5
P	AC-23A			
March Marc	Motor rating AC-23A, 50 - 60 Hz	Р	kW	
Sol V	230 V	Р	kW	3
File	400 V 415 V	Р	kW	5.5
Rated operational current motor load switch	500 V	Р	kW	7.5
1	690 V	Р	kW	5.5
March Marc	Rated operational current motor load switch			
S00 V	230 V	I _e	Α	13.3
Bill Part Bill	400 V 415 V	l _e	Α	13.3
SSO V	500 V	l _e	Α	13.3
DC-1_ Load-break switches L/R = 1 ms Ig	690 V		Α	7.6
DC-1, Load-break switches L/R = 1 ms				
Rated operational current				
Voltage per contact pair in series Voltage per contact pair in series Indicates In		l _e	Α	10
DC-21A				
Rated operational current		l _o	Α	
Contacts	Rated operational current			1
DC-23A, motor load switch L/R = 15 ms 24 V Rated operational current Contacts Rated operational current Rated operational current Rated operational current Is A 10 Contacts Contacts Contacts Rated operational current Is A 10 Contacts Contacts Contacts Rated operational current Is A 10 Contacts Contacts Contacts Rated operational current Is A 10 Contacts Contacts Quentity Rated operational current Is A 5 Contacts Contacts Quentity 3 240 V Rated operational current Is A 5 Contacts Quentity 3 Contacts Quentity 3 Contacts Quentity 5 Contacts Contacts Quentity 5 Contacts Quentity 5 Contacts Quentity 5 Contacts Quentity 5 Contacts Contacts Quentity 5 Contacts Contacts Pol-13. Contacts Pol-13. Contacts Pol-14. Contacts Pol-15. Contacts Rated operational current Is A 10 Quentity 5 Contacts Pol-15. Contacts Pol-16. Contacts Pol-16. Contacts Pol-17. Contacts Pol-18. Contacts Pol-18. Contacts Pol-19. Contacts Pol-		·e		
Rated operational current			Quantity	
Rated operational current				
Contacts 48 V Rated operational current 60 V Rated operational current 1e A 10 Contacts 60 V Rated operational current 1e A 10 Contacts Contacts 120 V Rated operational current 1		اه	Α	10
A8V Rated operational current Contacts 60 V Rated operational current Ie A Duantity Contacts		C		
Rated operational current			- Luumary	
Contacts		اه	Α	10
Rated operational current		-6		
Rated operational current Contacts 120 V Rated operational current Contacts 120 V Rated operational current Contacts 240 V Rated operational current Personal Contacts DC-13, Control switches L/R = 50 ms Rated operational current Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Pault probability Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Rated operational current Personal current Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current Personal Control circuit reliability at 24 V DC, 10 mA Rated operational current			Quantity	-
Contacts Rated operational current Rated operational current Contacts Quantity Rated operational current Rated operational current Rated operational current Rated operational current Contacts DC-13, Control switches L/R = 50 ms Rated operational current Voltage per contact pair in series Control circuit reliability at 24 V DC, 10 mA Fault probability Fault probability Terminal capacities Solid or stranded Final capacities Flexible with ferrules to DIN 46228 Terminal screw Tightening torque for terminal screw Tightening torque for terminal screw Technical safety parameters:		ام	Α	10
120 V Rated operational current Contacts Quantity Agency A 5 Quantity Agency A 10 Agency		C		
Rated operational current Contacts Quantity A 5 Quantity Bated operational current Quantity Contacts Quantity Contacts Quantity Contacts Quantity Contacts Quantity Contacts Quantity Contacts A 10 Voltage per contact pair in series V 32 Control circuit reliability at 24 V DC, 10 mA Fault probability Fault prob			- Luumany	
Contacts Quantity Rated operational current Ie Contacts DC-13, Control switches L/R = 50 ms Rated operational current Voltage per contact pair in series Control circuit reliability at 24 V DC, 10 mA Fault probability Fexible with ferrules to DIN 46228 Fixible with ferrules to DIN 46228 Terminal screw Tightening torque for terminal screw Technical safety parameters:		l _o	Α	5
Rated operational current Contacts COLTAGE BATE OPERATION SWITCHES L/R = 50 ms Rated operational current Voltage per contact pair in series Control circuit reliability at 24 V DC, 10 mA Fault probability Probability Frominal capacities Solid or stranded mm² 1 x (1 - 2,5) 2 x (1 - 2,5) 2 x (1 - 2,5) 2 x (0.75 - 2.5) 2 x (0.75 - 2.5) Terminal screw Terminal screw Tightening torque for terminal screw Nm 1 Technical safety parameters:		C		
Rated operational current Contacts DC-13, Control switches L/R = 50 ms Rated operational current Voltage per contact pair in series Control circuit reliability at 24 V DC, 10 mA Fault probability Terminal capacities Solid or stranded Solid or stranded Terminal screw Terminal screw Tightening torque for terminal screw Tightening torque for terminal screw Technical safety parameters:				
Contacts DC-13, Control switches L/R = 50 ms Rated operational current Voltage per contact pair in series Control circuit reliability at 24 V DC, 10 mA Fault probability Fault probability HF control circuit reliability at 24 V DC, 10 mA Fault probability Fault probability Fault probability HF control circuit reliability at 24 V DC, 10 mA Fault probability Fault probability HF control circuit reliability at 24 V DC, 10 mA Fault probability HF control circuit reliability at 24 V DC, 10 mA mm² 1 x (1 - 2,5) 2 x (1 - 2,5) 2 x (1 - 2,5) 2 x (0.75 - 2.5) 2 x (0.75 - 2.5) 2 x (0.75 - 2.5) Terminal screw M3.5 Tightening torque for terminal screw Technical safety parameters:		l _e	A	5
DC-13, Control switches L/R = 50 ms Rated operational current Voltage per contact pair in series Control circuit reliability at 24 V DC, 10 mA Fault probability Terminal capacities Solid or stranded Solid or stranded Flexible with ferrules to DIN 46228 Terminal screw Tightening torque for terminal screw Technical safety parameters:		.6		
Rated operational current Voltage per contact pair in series Control circuit reliability at 24 V DC, 10 mA Fault probability Terminal capacities Solid or stranded mm² 1 x (1 - 2,5) 2 x (1 - 2,5) 2 x (1 - 2,5) 2 x (0.75 - 2.5) 2 x (0.75 - 2.5) Terminal screw Tightening torque for terminal screw Nm 1 Technical safety parameters:			Quantity	
Voltage per contact pair in series Control circuit reliability at 24 V DC, 10 mA Fault probability Terminal capacities Solid or stranded mm² 1 x (1 - 2,5) 2 x (1 - 2,5) 2 x (1 - 2,5) 2 x (0.75 - 2.5) 2 x (0.75 - 2.5) 2 x (0.75 - 2.5) Terminal screw Tightening torque for terminal screw Nm 1 Technical safety parameters:		اه	Α	10
Control circuit reliability at 24 V DC, 10 mA Fault probability Fault probability Fault probability HF < 10 ⁻⁵ ,< 1 failure in 100,000 switching operations Terminal capacities Solid or stranded mm² 1 x (1 - 2,5) 2 x (1 - 2,5) 2 x (1 - 2,5) 1 x (0.75 - 2.5) 2 x (0.75 - 2.5) 2 x (0.75 - 2.5) Terminal screw Tightening torque for terminal screw Nm 1 Technical safety parameters:		^e		
Terminal capacities Solid or stranded mm² 1 x (1 - 2,5) 2 x (1 - 2,5) 2 x (1 - 2,5) 2 x (0.75 - 2.5) Terminal screw Tightening torque for terminal screw Nm 1 Technical safety parameters:		Fault		
Solid or stranded $mm^2 = \frac{1 \times (1 - 2.5)}{2 \times (1 - 2.5)}$ Flexible with ferrules to DIN 46228 $mm^2 = \frac{1 \times (0.75 - 2.5)}{2 \times (0.75 - 2.5)}$ Terminal screw $M3.5$ Tightening torque for terminal screw $Nm = 1$ Technical safety parameters:			i i F	< 10 °,< 1 failure in 100,000 switching operations
Flexible with ferrules to DIN 46228 mm² 1 x (0.75 - 2.5) 2 x (0.75 - 2.5) 2 x (0.75 - 2.5) Terminal screw M3.5 Tightening torque for terminal screw Nm 1 Technical safety parameters:				
Flexible with ferrules to DIN 46228 mm² 1 x (0.75 - 2.5) 2 x (0.75 - 2.5) Terminal screw M3.5 Tightening torque for terminal screw Nm 1 Technical safety parameters:	Solid or stranded		mm ²	1 x (1 - 2,5) 2 x (1 - 2,5)
Terminal screw M3.5 Tightening torque for terminal screw Nm 1 Technical safety parameters:	Flexible with ferrules to DIN 46228		mm ²	1 x (0.75 - 2.5)
Technical safety parameters:	Terminal screw			
Technical safety parameters:			Nm	
Notes B10 _d values as per EN ISO 13849-1, table C1	Notes			B10 _d values as per EN ISO 13849-1, table C1

Rating data for approved types

Kating data for approved types			
Contacts			
Rated operational voltage	$U_{\rm e}$	V AC	600
Rated uninterrupted current max.			
Main conducting paths			
General use		Α	16
Auxiliary contacts			
General Use	I _U	Α	10
Pilot Duty			A 600 P 300
Switching capacity			
Maximum motor rating			
Single-phase			
120 V AC		HP	0.5
200 V AC		HP	1
240 V AC		HP	1.5
Three-phase			
200 V AC		HP	3
240 V AC		HP	3
480 V AC		HP	7.5
600 V AC		HP	7.5
Short Circuit Current Rating		SCCR	
Basic Rating		kA	5
max. Fuse		Α	50
High fault rating		kA	10
max. Fuse		Α	20, Class J
Terminal capacity			
Solid or flexible conductor with ferrule		AWG	18 - 14
Terminal screw			M3.5
Tightening torque		lb-in	8.8

Design verification as per IEC/EN 61439

echnical data for design verification			
Rated operational current for specified heat dissipation	In	Α	20
Heat dissipation per pole, current-dependent	P _{vid}	W	0.6
Equipment heat dissipation, current-dependent	P _{vid}	W	0
Static heat dissipation, non-current-dependent	P_{vs}	W	0
Heat dissipation capacity	P _{diss}	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	50
C/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
$10.2.3.3\mbox{Verification}$ of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.

10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9 Insulation properties	
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Control switch (EC002611)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Control switch (ecl@ss10.0.1-27-37-14-14 [ACN998011])

Type of switch		Reverser
Number of poles		4
Max. rated operation voltage Ue AC	V	690
Rated permanent current lu	Α	20
Number of switch positions		3
With 0 (off) position		Yes
With retraction in 0-position		Yes
Device construction		Built-in device
Width in number of modular spacings		4
Suitable for ground mounting		Yes
Suitable for front mounting 4-hole		No
Suitable for distribution board installation		Yes
Suitable for intermediate mounting		No
Complete device in housing		No
Type of control element		Toggle
Front shield size		Other
Degree of protection (IP), front side		IP30
Degree of protection (NEMA), front side		Other

Approvals

• •	
Product Standards	UL 60947-4-1;CSA - C22.2 No. 60947-4-1-14; CSA-C22.2 No. 94; IEC/EN 60947-3; CE marking
UL File No.	E36332
UL Category Control No.	NLRV
CSA File No.	12528
CSA Class No.	3211-05
North America Certification	UL listed, CSA certified
Suitable for	Branch circuits, suitable as motor disconnect
Degree of Protection	IEC: IP30; UL/CSA Type: –

Dimensions

