DATASHEET - T0-6-15151/E



Step switches, T0, 20 A, flush mounting, 6 contact unit(s), Contacts: 12, 45 °, maintained, Without 0 (Off) position, 1-4, design no. 15151



Part no. Catalog No. T0-6-15151/E 015368

Similar to illustration

Delivery program			
Product range			Control switches
Part group reference			то
Basic function			Step switches
			with black thumb grip and front plate
Contacts			12
Degree of Protection			Front IP65
Design			flush mounting
Contact sequence			
Switching angle		o	45
Switching performance			maintained Without 0 (Off) position
Design number			15151
Front plate no.			FS 406
front plate			1-4
Motor rating AC-23A, 50 - 60 Hz			
400 V	Р	kW	5.5
Rated uninterrupted current	lu	A	20
Note on rated uninterrupted current !u			Rated uninterrupted current ${\rm I}_{\rm u}$ is specified for max. cross-section.
Number of contact units		contact unit(s)	6
		0(0)	
Technical data General			
Standards			IEC/EN 60947, VDE 0660, IEC/EN 60204, CSA, UL

Open		°C	-25 - +50
Enclosed		°C	-25 - +40
Overvoltage category/pollution degree		-	III/3
Rated impulse withstand voltage	U _{imp}	V AC	6000
Mechanical shock resistance	Cimp		15
Mounting position		g	As required
Contacts			As required
Electrical characteristics			
Rated operational voltage	Ue	V AC	690
Rated uninterrupted current	l _u	A	20
Note on rated uninterrupted current !u	·u		Rated uninterrupted current I _u is specified for max. cross-section.
Load rating with intermittent operation, class 12			
AB 25 % DF		x l _e	2
AB 40 % DF		x l _e	1.6
AB 60 % DF		x I _e	1.3
Short-circuit rating			
Fuse		A gG/gL	
Rated short-time withstand current (1 s current)	I _{cw}	A _{rms}	320
Note on rated short-time withstand current lcw			Current for a time of 1 second
Rated conditional short-circuit current	Ι _q	kA	6
Switching capacity			
$\cos \phi$ rated making capacity as per IEC 60947-3		A	130
Rated breaking capacity $\cos \phi$ to IEC 60947-3		A	
230 V		A	100
400/415 V		A	110
500 V		A	80
690 V		A	60
Safe isolation to EN 61140			
between the contacts		V AC	440
Current heat loss per contact at I _e		W	0.6
Current heat loss per auxiliary circuit at I _e (AC-15/230 V)		CO	0.6
Lifespan, mechanical	Operations	x 10 ⁶	> 0.4
Maximum operating frequency	Operations/h		1200
AC			
AC-3			
Rating, motor load switch	Р	kW	
220 V 230 V	Р	kW	3
230 V Star-delta	Р	kW	5.5
400 V 415 V	Р	kW	5.5
400 V Star-delta	Р	kW	7.5
500 V	Ρ	kW	5.5
500 V Star-delta	Р	kW	7.5
690 V	Р	kW	4
690 V Star-delta	Р	kW	5.5
Rated operational current motor load switch			
230 V	le	A	11.5
230 V star-delta	le	A	20
400V 415 V	l _e	A	11.5
400 V star-delta	l _e	A	20
500 V		A	9
	l _e		
500 V star-delta	l _e	A	15.6
690 V	le	A	4.9
690 V star-delta	l _e	А	8.5
AC-23A			

22VPWS00V 15VPV300V 15VPV395VPV395VPV395VVN395VVN395VVN395VVN395VVN395VVN395VVN395VVN395VVN395VVN395VVN395VVN395VVN395VVN395VNN3	Motor rating AC-23A, 50 - 60 Hz	Р	kW	
Add variablePNMNBV 435NASBV 435NANABV				3
Set SystemPNMSRest SystemPNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNSSystemNNNSystemN				
NoteNo				
Ried operational current mode (add operational cur				
281°463.3340°3.33.3540°43.3640°43.36543.36543.36555.143.36555.143.36555.143.365.155.143.37000000000000000000000000000000000000			KVV	
400 418 V4A83900 418 V1033900 400 400 400 400 400 400 400 400 400		1	Δ	13.3
SNVRRRRRGNVKAAGNUK <td< td=""><td></td><td></td><td></td><td></td></td<>				
indiceindiceindice0IndiceIndiceRadioperion learningIndiceIndiceRadioperion learningIndiceIndiceRadioperion learningIndiceIndiceRadioperion learningIndiceIndice0IndiceIndice </td <td></td> <td></td> <td></td> <td></td>				
DCImage of contracts and arrentImage of contracts and arrent ar				
SectorSectorSectorSectorSectorNotage restands around a sectorRRRNotage restands around a sectorRRRSector		l _e	A	7.6
Rate operational currentInAABated operational currentInABated operational currentInABated operational currentInABated operational currentInABated operational currentInABated operational currentInInBated operational currentInInDi In <t< td=""><td></td><td></td><td></td><td></td></t<>				
Webso per contact pair nervesIV0DCAAIIIRated operational currentIIIContactsIIIDCAAIIIDCAAIIIDCAAIIIDCAAIIIStational currentIIIStational currentIIIStat				
DC 2AIARed dependence functional server functional	Rated operational current	le	A	10
Rated operational current I Au I DC 23A motor load switch L/R = 15 ms I I I 3A V I I I A Reid operational current I I I Rated operational current I I I A Reid operational current I I I Rated operational current I I<	Voltage per contact pair in series		V	60
Centeds Centers	DC-21A	۱ _e	A	
DC23A, moories awith L/R = 15 ms Image generational curvant Image generational curv	Rated operational current	۱ _e	А	1
24VAed garational currentAeg Aed garational currentAeg Aeg Aeg Aeg Aeg Aeg Aeg Aeg Aeg Aeg	Contacts		Quantity	1
i ated operational currenti, iAi Cancelonational currenti Reid operational currentiiii Rei	DC-23A, motor load switch $L/R = 15 \text{ ms}$			
IchairsIchairsIchairs48 vAAAsted parational currentAAContactsAARated porational currentKARated porational currentKARated porational currentKAContactsKARated porational currentKARated operational currentKKRated operational curren	24 V			
f BVImage: persional currentImage: persional currentImag	Rated operational current	le	A	10
Rated operational currentP 0A 0P 0ContractsN 0N 0N 0Rated operational currentN 0N 0N 0120 VN 0N 0N 0200 VN 0N 0N 0 <t< td=""><td>Contacts</td><td></td><td>Quantity</td><td>1</td></t<>	Contacts		Quantity	1
ContactsCountCountCount60 VKKKRated operational currentKKManual120 VKKManual120 VKKM120 VKMM120 VKMM120 VKMM120 VKMM120 VKMM120 VKMM120	48 V			
bVImage: bot of the section of the secti	Rated operational current	l _e	A	10
bVImage: bot of the section of the secti	Contacts		Quantity	2
IndexIndexIndexIndex120 VIndexIndexIndexAtada operational currentIndexIndexIndexAtada operational currentIndexIndexIndexAtada operational currentIndexIndexIndexIndex operational current maxIndexIndexIndexIndex operational current maxIndexIndexIndexI	60 V			
IndexIndexIndexIndex120 VIndexIndexIndexAtada operational currentIndexIndexIndexAtada operational currentIndexIndexIndexAtada operational currentIndexIndexIndexIndex operational current maxIndexIndexIndexIndex operational current maxIndexIndexIndexI		او	A	10
12011200120012001200Atad operational currentPA52400ContratisGuantay5Atad operational currentPGuantay5TochatasGuantay5ContratisDortata Sourcol switches L/R = 50 msPPPNotage per conscipativi seriesP0SOutroit circuit raibility at 24 VDC, 10 mAPNSPortinal capacitiesPNSTerminal capacitiesPNSFerdinal seriesPNSFlorid sind strandedPNSTotale strandedPNSTerminal capacitiesPNSTerminal capacitiesPNSTerminal capacitiesPNSTerminal capacitiesPNSTerminal capacitiesPNSTerminal capacitiesPNSTerminal capacitiesPNNTerminal capacitiesNNNTerminal capacitiesNNNTerminal capacitiesNNNTerminal capacitiesNNNTerminal capacitiesNNNTerminal capacitiesNNNTerminal capacitiesNNNTerminal capacitiesNNNTerminal capacitiesNNNTerminal capacit		U C	Quantity	3
Rated operational currentInRatedResult			addinary	
Contacts Image: Section of the sectin of the sectin of the section of the section of the section of t		ام	А	5
20V A A Rated operational current Quanti S Contacts Quanti S DC-13, Control switches L/R = 50 ms A S Rated operational current A D Voltage per contact pair in series A S Control circuit reliability at 24 VDC, 10 mA A D Forbial contact series V S Terminal capacities N S		C		
Rated operational current Image: space			addinary	
Contacts Manual Mathematical M		la	Δ	5
Dc-13, Control switches L/R = 50 ms Image: Mathematical Science of Sci		·e		
Rated operational currentI eAIVottage per contact pair in seriesFault probabilityV3Control circuit reliability at 24 V DC, 10 mAFault probabilityHe probability10 \$^{5}\$ 1 failure in 100,000 switching operationsTerminal capacitiesI probabilityI (1 2.5) 2.x (1 - 2.5) 2.x (1 - 2.5)Fexible with ferrules to DIN 46228mar probability1x (0.75 - 2.5) 2.x (0.75 - 2.5)Terminal capacitiesMar probability1x (0.75 - 2.5) 2.x (0.75 - 2.5)Terminal screwMar probabilityMar probabilityTeghtania proved for perminal screwMar probabilityMar probabilityTechnical safety parameters:Mar probabilityMar probabilityContactsMar per streinMar per streinRated operational voltageMar per streinMar per streinMain conducting pathsMar per streinMar per strein			Quantity	
Votage per contact pair in series V 2 Control circuit reliability at 24 V DC, 10 mA Fault probability Fault probability Fault probability V a Terminal capacities E I 1/1 - 2,5 x			٨	10
Control circuit reliability at 24 VDC, 10 mA Fault probability Hr clo ⁵ , 1 failure in 100,000 switching operations Terminal capacities Terminal capacities Terminal capacities Solid or stranded Image: Provide Capacity Provide Cap		'e		
Terminal capacities Solid or stranded I × (1 - 2,5) × (1 - 2,5) × (1 - 2,5) Flexible with ferrules to DIN 46228 I × (0,75 - 2,5) × (0,75 - 2,5) Terminal screw I × (0,75 - 2,5) Terminal screw Mm ² I × (0,75 - 2,5) Tightening torpute for terminal screw Mm ² Mu Tightening torpute for terminal screw Mm ² Mu Tightening torpute for terminal screw Mu Mu Tightening torpute for terminal screw Mu Mu Terminal screw Mu Mu Mu Terminal screw Mu Mu Mu Mu Terminal screw Mu		F b		
Solid or stranded mm² 1× (1 - 2.5) Flexible with ferrules to DIN 46228 mm² 1× (0.75 - 2.5) Terninal screw Mm² 1× (0.75 - 2.5) Togthening torque for terminal screw Mm² Ma5 Togthening torque for terminal screw Mm² Ma5 Technical safety parameters: Mm² Ma5 Technical safety parameters: Mm² Ma1 Technical safety parameters: Mm² Ma1 values as per EN ISO 13849-1, table C1 Rating data for approved types Ma1 Ma1 Contacts Ma1 Ma1 Rated operational voltage Mu Ma1 Main conducting paths Mu Ma1 Main conducting paths Ma1 Ma1 Auxiliary contacts Mu Ma1 General Use Mu Ma1	Control circuit reliability at 24 V DC, 10 mA		HF	< 10 ⁻⁵ ,< 1 failure in 100,000 switching operations
Flexible with ferrules to DIN 46228 mm 2 x (1 - 2,5) Terminal screw mm² 1 x (0.75 - 2.5) Terminal screw M3.5 Tightening torque for terminal screw Mm 1 Technical safety parameters: Mm 10 Technical safety parameters: Mm 10 Rated operational voltage Main Main Rated operational voltage Main Main Main conducting paths Main Main General use Main Main Auxiliary contacts Main Main Jeneral Use June Main	Terminal capacities			
Flexible with ferrules to DIN 46228 ann ² ix (0.75 - 2.5) Terminal screw M3.5 Tightening torque for terminal screw Nm i Actional screw Technical safety parameters: Nm i Actional screw Totacia Screw Screw Notes Screw Screw Rated operational voltage Main conducting paths Screw Main conducting paths Yace Screw General use Yace Screw General use Yace Screw Senderal use Yace Screw General Use Yace Screw Senderal Use Yace Screw	Solid or stranded		mm ²	
Terminal screw 2x (0.75 - 2.5) Terminal screw M3.5 Tightening torque for terminal screw Nm 1 Technical safety parameters: Nm 1 Technical safety parameters: Nm 10d values as per EN ISO 13849-1, table C1 Rating data for approved types Song Song Contacts Image: Song Song Rated operational voltage Veg Main conducting paths Main conducting paths Image: Song Song General use Image: Song Nm Auxiliary contacts Image: Song Song Image: Song Image: Song Song Image: Song Image: Song Song	Flouible with formulae to DIN 4000		2	
Tightening torque for terminal screw Nm 1 Tightening torque for terminal screw Nm 1 Technical safety parameters: Nm Nm Notes Image: Streme Screw Nm Rating data for approved types Image: Streme Screw Nm Contacts Image: Streme Screw Nm Rated operational voltage Image: Streme Screw Nm Rated uninterrupted current max. Image: Streme Screw Nm Main conducting paths Image: Streme Screw Image: Streme Screw General use Image: Streme Screw Image: Streme Screw Main general Use Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme Screw Image: Streme	ו ופאושופ איננו ופורטופא נט טווא 40220		mm²	
Technical safety parameters: Notes Image: Section of the section	Terminal screw			M3.5
Technical safety parameters: Notes Image: Section of the section	Tightening torque for terminal screw		Nm	1
Rating data for approved types Contacts Image: Contact sector s	Technical safety parameters:			
Contacts Image: Contact set of the s				B10 _d values as per EN ISO 13849-1, table C1
Rated operational voltage Ue V AC 600 Rated uninterrupted current max. Main conducting paths Main conducting paths Main conducting paths General use Auxiliary contacts A A General Use Iu A Iu	Rating data for approved types			
Rated uninterrupted current max. Part Part Part Part Part Part Part Part				
Main conducting paths Image: Constraint of the second of	Rated operational voltage	U _e	V AC	600
General use A A Auxiliary contacts I I General Use Iu A	Rated uninterrupted current max.			
Auxiliary contacts Image: Contact set of the se	Main conducting paths			
General Use IU A 10	General use		А	16
	Auxiliary contacts			
Pilot Duty A 600	General Use	lu	А	10
	Pilot Duty			A 600

		P 300
Switching capacity		
Maximum motor rating		
Single-phase		
120 V AC	HP	0.5
200 V AC	HP	1
240 V AC	HP	1.5
Three-phase		
200 V AC	HP	3
240 V AC	HP	3
480 V AC	HP	7.5
600 V AC	HP	7.5
Short Circuit Current Rating	SCCR	
Basic Rating	kA	5
max. Fuse	А	50
High fault rating	kA	10
max. Fuse	А	20, Class J
Terminal capacity		
Solid or flexible conductor with ferrule	AWG	18 - 14
Terminal screw		M3.5
Tightening torque	lb-in	8.8

Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	l _n	Α	20
Heat dissipation per pole, current-dependent	P _{vid}	W	0.6
Equipment heat dissipation, current-dependent	P _{vid}	W	0
Static heat dissipation, non-current-dependent	P _{vs}	W	0
Heat dissipation capacity	P _{diss}	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	50
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			UV resistance only in connection with protective shield.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Control switch (EC002611)


Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Control switch (ecl@ss10.0.1-27-37-14-14	
[ACN998011])	


Type of switch		Level switch
Number of poles		3
Max. rated operation voltage Ue AC	V	690
Rated permanent current lu	А	20
Number of switch positions		4
With 0 (off) position		No
With retraction in 0-position		No
Device construction		Built-in device
Width in number of modular spacings		0
Suitable for ground mounting		No
Suitable for front mounting 4-hole		Yes
Suitable for distribution board installation		No
Suitable for intermediate mounting		No
Complete device in housing		No
Type of control element		Toggle
Front shield size		48x48 mm
Degree of protection (IP), front side		IP65
Degree of protection (NEMA), front side		12

Approvals

UL 60947-4-1;CSA - C22.2 No. 60947-4-1-14; CSA-C22.2 No. 94; IEC/EN 60947-3; CE marking
E36332
NLRV
12528
3211-05
UL listed, CSA certified
Branch circuits, suitable as motor disconnect
IEC: IP65; UL/CSA Type 1, 12
N 12 32 UI B

Dimensions





(2) ZFS-... Label mount not included as standard