## **DATASHEET - T3-4-15374/XZ**



T3, 32 A, rear mounting, Basic switch, 4 contact unit(s), Contacts: 8, 45 °, design no. 15374



 Part no.
 T3-4-15374/XZ

 Catalog No.
 020179

Delivery program			
Product range			Control switches
Part group reference			Т3
Contacts			8
Design			rear mounting Basic switch
Contact sequence			$ \begin{array}{cccccccccccccccccccccccccccccccccccc$
Switching angle		•	45
Design number			15374
Front plate no.			<sup>2</sup> <sup>0</sup> <sup>1</sup> FS 458
Motor rating AC-23A, 50 - 60 Hz			
400 V	Ρ	kW	15
Rated uninterrupted current	l <sub>u</sub>	Α	32
Note on rated uninterrupted current $!_u$			Rated uninterrupted current $\boldsymbol{I}_{\boldsymbol{u}}$ is specified for max. cross-section.
Number of contact units		contact unit(s)	4

## **Technical data**

General			
Standards			IEC/EN 60947, VDE 0660, IEC/EN 60204 Switch-disconnector according to IEC/EN 60947-3
Climatic proofing			Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30
Ambient temperature			
Open		°C	-25 - +50
Enclosed		°C	-25 - +40
Overvoltage category/pollution degree			111/3
Rated impulse withstand voltage	U <sub>imp</sub>	V AC	6000
Mechanical shock resistance		g	15
Mounting position			As required

#### **Contacts**

Electrical characteristics			
Rated operational voltage	U <sub>e</sub>	V AC	690
Rated uninterrupted current	lu	A	32
Note on rated uninterrupted current $\boldsymbol{!}_u$			Rated uninterrupted current $\mathbf{I}_{\mathbf{u}}$ is specified for max. cross-section.
Load rating with intermittent operation, class 12			
AB 25 % DF		x I <sub>e</sub>	2
AB 40 % DF		x I <sub>e</sub>	1.6
AB 60 % DF		x l <sub>e</sub>	1.3
Short-circuit rating			
Fuse		A gG/gL	35
Rated short-time withstand current (1 s current)	I <sub>cw</sub>	A <sub>rms</sub>	650
Note on rated short-time withstand current lcw			Current for a time of 1 second
Rated conditional short-circuit current	lq	kA	1
Switching capacity	ч		
cos φ rated making capacity as per IEC 60947-3		А	320
Rated breaking capacity $\cos \phi$ to IEC 60947-3		A	
230 V		A	260
400/415 V		A	260
500 V		A	240
690 V		A	170
Safe isolation to EN 61140			
between the contacts		V AC	440
Current heat loss per contact at l <sub>e</sub>		W	1.1
Current heat loss per auxiliary circuit at I <sub>e</sub> (AC-15/230 V)		CO	1.1
Lifespan, mechanical	Operations	x 10 <sup>6</sup>	> 0.5
		X IU	
Maximum operating frequency AC	Operations/h		1200
AC-3			
	Р	kW	
Rating, motor load switch 220 V 230 V	P	kW	5.5
230 V Star-delta	P	kW	7.5
400 V 415 V	P	kW	11
400 V Star-delta	P	kW	15
400 V Stat-deita 500 V	P	kW	15
500 V Star-delta	P		
	P	kW	18.5
690 V		kW	11
690 V Star-delta	Р	kW	22
Rated operational current motor load switch		٨	22.7
230 V	l <sub>e</sub>	A	23.7
230 V star-delta	l <sub>e</sub>	A	32
400V 415 V	l <sub>e</sub>	A	23.7
400 V star-delta	le	А	32
500 V	l <sub>e</sub>	А	23.7
500 V star-delta	l <sub>e</sub>	А	32
690 V	l <sub>e</sub>	А	14.7
690 V star-delta	l <sub>e</sub>	A	25.5
AC-23A			
Motor rating AC-23A, 50 - 60 Hz	Р	kW	
230 V	Р	kW	7.5
400 V 415 V	Р	kW	15
500 V	P	kW	15
500 V 690 V	-		15 15

230 V	I <sub>e</sub>	А	32
400 V 415 V	l <sub>e</sub>	A	32
500 V	l <sub>e</sub>	A	26.4
690 V	le	A	17
DC			
DC-1, Load-break switches L/R = 1 ms			
Rated operational current	۱ <sub>e</sub>	A	25
Voltage per contact pair in series		V	60
DC-21A	l <sub>e</sub>	А	
Rated operational current	I <sub>e</sub>	А	1
Contacts		Quantity	1
DC-23A, motor load switch L/R = 15 ms			
24 V			
Rated operational current	Ι <sub>e</sub>	А	25
Contacts		Quantity	1
48 V			
Rated operational current	l <sub>e</sub>	A	25
Contacts		Quantity	2
60 V			
Rated operational current	le	A	25
Contacts		Quantity	3
120 V			
Rated operational current	l <sub>e</sub>	A	12
Contacts		Quantity	3
240 V			
Rated operational current	I <sub>e</sub>	A	5
Contacts		Quantity	5
DC-13, Control switches L/R = 50 ms			
Rated operational current	l <sub>e</sub>	A	20
Voltage per contact pair in series		V	24
Control circuit reliability at 24 V DC, 10 mA	Fault	H <sub>F</sub>	< 10 <sup>-5</sup> ,< 1 failure in 100,000 switching operations
Terminal experities	probability		
Terminal capacities Solid or stranded		mm <sup>2</sup>	1 x (1 - 6)
Solid S. Strandou		mm <sup>-</sup>	$2 \times (1 - 6)$
Flexible with ferrules to DIN 46228		mm <sup>2</sup>	1 x (0.75 - 4) 2 x (0.75 - 4)
Terminal screw			M4
Tightening torque for terminal screw		Nm	1.6
Technical safety parameters:			
Notes			B10 <sub>d</sub> values as per EN ISO 13849-1, table C1
Rating data for approved types			
Terminal capacity			
Terminal screw			M4

# Design verification as per IEC/EN 61439

Technical data for design verification			
Rated operational current for specified heat dissipation	In	А	32
Heat dissipation per pole, current-dependent	P <sub>vid</sub>	W	1.1
Equipment heat dissipation, current-dependent	P <sub>vid</sub>	W	0
Static heat dissipation, non-current-dependent	P <sub>vs</sub>	W	0
Heat dissipation capacity	P <sub>diss</sub>	W	0
Operating ambient temperature min.		°C	-25
Operating ambient temperature max.		°C	50
EC/EN 61439 design verification			
10.2 Strength of materials and parts			

Meets the product standard's requirements.
Meets the product standard's requirements.
Meets the product standard's requirements.
Meets the product standard's requirements.
UV resistance only in connection with protective shield.
Does not apply, since the entire switchgear needs to be evaluated.
Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
Meets the product standard's requirements.
Does not apply, since the entire switchgear needs to be evaluated.
Does not apply, since the entire switchgear needs to be evaluated.
Is the panel builder's responsibility.
Is the panel builder's responsibility.
Is the panel builder's responsibility.
Is the panel builder's responsibility.
Is the panel builder's responsibility.
The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
Is the panel builder's responsibility. The specifications for the switchgear must be observed.
Is the panel builder's responsibility. The specifications for the switchgear must be observed.
The device meets the requirements, provided the information in the instruction

### **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Control switch (EC002611) Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Control switch (ecl@ss10.0.1-27-37-14-14 [ACN998011]) On/Off switch Type of switch Number of poles 4 ٧ Max. rated operation voltage Ue AC 690 Rated permanent current lu А 32 Number of switch positions 3 With 0 (off) position Yes Yes With retraction in 0-position Built-in device Device construction Width in number of modular spacings 0 Suitable for ground mounting Yes Suitable for front mounting 4-hole No Suitable for distribution board installation No Suitable for intermediate mounting Yes Complete device in housing No Other Type of control element Front shield size Other Degree of protection (IP), front side IP00 Degree of protection (NEMA), front side Other