


ACCESSORIES

1- AND 2-LEVEL WIRELESS REPEATERS FRP61-230V



Manuals and documents in further languages:
<http://eltako.com/redirect/FRP61-230V>

FRP61-230V



1 and 2 level wireless repeaters. Only 0.7 watt standby loss.

For installation. 45 mm long, 45 mm wide, 33 mm deep.

Supply voltage 230 V.

This repeater is only needed if the building conditions prevent undisturbed reception or the distance between the wireless pushbutton and receiver is too great.

The 1-level mode is activated ex works. Only wireless signals from sensors are received, tested and retransmitted at full transmit power. Wireless signals from other repeaters are ignored to reduce the data volume.

Use the rotary switch to switch over to 2 level mode. Then the wireless signals from sensors and from another 1 level repeater are processed. A signal may therefore be received and amplified twice.

The LED indicates incoming wireless signals by flashing briefly.

Wireless repeaters need not be taught-in. They receive and amplify signals from all wireless sensors within their reception area.

FRP61-230V	1- and 2-level wireless repeater	Art. No. 30000350	
-------------------	----------------------------------	--------------------------	--