



## PRIMETAB S11B

### Hardware

Processor (CPU)	Intel® Celeron® N3350 processor (up to 2.4 GHz, 2 MB Intel® Smart-Cache) dual core
Operating system	Windows 10 Home in S mode
Office	Office 365 Personal (one-year-license) <sup>1</sup>
RAM	4 GB
Internal storage	64 GB <sup>2</sup>
Graphic Unit (GPU)	Intel® HD Graphics 500
Display size	29.5 cm (11.6")
Display type	10-point capacitive multi-touch Full-HD-IPS-display
Screen resolution	1920 x 1080 pixel
Aspect ratio	16:9
Camera	Front: 2 MP
Speaker	Stereo
Microphone	yes
Interface	2 x USB 3.0, 1 x Mini-HDMI®, memory card reader, audio out/mic in (3.5 mm)
Network	WiFi, Bluetooth 4.2
Frequencies	WiFi IEEE 802.11b/g/n/ac: 2.4 GHz/5 GHz
Memory extension	microSD(HC/XC) up to 256 GB
Dimensions	approx. 290 mm x 180 mm x 9 mm
Weight	approx. 780 g (tablet), approx. 275 g (Keyboard)
Housing material	aluminium, plastic
Color	Grey

## PRIMETAB S11B

### Record and playback

Playable video formats	MPEG-4.10 H.264/AVC (MP@L4.1, HP@L4.0), MPEG-4.2 SP/ASP (e.g. Xvid)
Video container formats	AVI, MKV, MOV
Gaming	3D games, Classic games
Supported picture formats	JPEG, PNG, GIF, BMP
Playable audio formats	MP3, WAV, OGG, FLAC, AAC

### Battery and power supply

Type of battery	Lithium polymer
Capacity of battery	7.4 V / 4000 mAh / 29.60 Wh
Charge by	DC IN
Power supply	230 V (110 V - 240 V)

### Other characteristics

More	Hall-sensor
Languages	Multilanguage support by Windows 10
Package contents	Primetab S11B, power adapter (100 V - 240 V), cleaning cloth, quick guide, important safety and legal information

### Operation and storage

Temperatures	5° C to 30° C
Relative humidity	30 % to 70 %

<sup>1</sup>Office 365 Personal for 12 months included, software is already pre-installed. Office activation is required within 6 months of Windows activation date. After expiration, the license must be renewed for a fee.

<sup>2</sup>1 GB = 1 000 000 000 Bytes.

Memory card not included in the delivery.  
The battery in this product cannot be easily replaced by users themselves.  
We reserve the right to make changes and corrections.