GOOD WILL INSTRUMENT CO., LTD. N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

G<u><u></u>UINSTEK</u>

GPT-15000 Specifications

The specifications apply when the GPT-15000 is powered on for at least 30 minutes under +15°C~+35°C

GPT-15004 (Front)







GPT-15004 (Rear)



GPT-15003/15002/15001 (Rear)



(All models are available with optional GPIB or LAN)

Model \ Func.	AC Withstanding	DC Withstanding	Insulation Resistance	Ground Bond	Ground Continuity
GPT-15001	٧*				v
GPT-15002	٧*	V			v
GPT-15003	٧*	V	v		v
GPT-15004	٧*	V	V	V	V

* : Short current > 200mA

AC WITHSTANDING		
Output-Voltage Range	0.050kV~5.000kV	
Output-Voltage Resolution	1V	
Output-Voltage Accuracy	\pm (1% of setting + 5V) [no load]	
Maximum Rated Load	500 VA (5kV/100mA)	
Maximum Rated Current	100mA (0.5kV< V ≦5kV)	
	10mA (0.05kV \leq V \leq 0.5kV)	
Output-Voltage Waveform	Sine wave	
Output-Voltage Frequency	50 Hz / 60 Hz selectable	
Voltage Regulation	\pm (1% + 5V) [maximum rated load $ ightarrow$ no load]	
Voltmeter Accuracy	\pm (1% of reading + 5V)	
Current Measurement Range	1μA~100.0mA	
Current Best Resolution	1μΑ / 10μΑ / 100μΑ	
Current Measurement Accuracy	\pm (1.5% of reading + 30 μ A)	
Current Offset	60μA Maximum	
Window Comparator Method	Yes	
ARC Detect	Yes	
RAMP UP (Rise Time)	0.1s~999.9s	
RAMP DOWN (Fall Time)	0.0s~999.9s	

GOOD WILL INSTRUMENT CO., LTD.

N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

G<u><u></u></u>INSTEK

		· · · · · · · · · · · · · · · · · · ·	
TIMER (Test Time)*		OFF, 0.3s~999.9s	
TIMER Accuracy		±(100ppm + 20ms)	
WAIT TIME		0.0s~999.9s	
GND		ON/OFF	
DC WITHSTANDING			
Output-Voltage Range		0.050kV~6.000kV	
Output-Voltage Resoluti	on	1V	
Output-Voltage Accurac		± (1% of setting + 5V) [no load]	
Maximum Rated Load		100W (5kV/20mA)	
Maximum Rated Current		$20mA (0.5kV < V \le 6kV)$	
	·	$2mA (0.05kV \le V \le 0.5kV)$	
		$\pm (1\% + 5V)$ [maximum rated load \rightarrow no load]	
Voltage Regulation			
Voltmeter Accuracy		± (1% of reading + 5V)	
Current Measurement Range		1μA~20.00mA	
Current Best Resolution		0.1μΑ /1μΑ /10μΑ	
Current Measurement A	Accuracy	\pm (1.5% of reading + 3 μ A) when I Reading < 1mA	
		\pm (1.5% of reading + 30 μ A) when I Reading \geq 1mA	
Current Offset		5μA Maximum	
Window Comparator M	ethod	Yes	
ARC Detect		Yes	
RAMP UP (Rise Time)		0.1s~999.9s	
RAMP DOWN (Fall Time	e)	0.0s~999.9s	
TIMER (Test Time)*		OFF, 0.3s~999.9s	
TIMER Accuracy		±(100ppm + 20ms)	
WAIT TIME		0.0s~999.9s	
GND		ON/OFF	
INSULATION RESISTANC	E		
Output Voltage	_	50V~1200V dc	
Output-Voltage Resoluti	on	50V	
Output-Voltage Accuracy		± (1% of setting + 5V) [no load]	
Resistance Measurement			
Test Voltage	Display Range	Measurement Range / Accuracy	
-	0.1MΩ~ 10.00GΩ	$0.1M\Omega^{-1}M\Omega : \pm (5\% \text{ of reading + 3 count})$	
50V≦V≦100V	0.11012 10.00312		
150V≤V≤450V	0.1MΩ~ 20.00GΩ	1 MΩ~50MΩ : \pm (5% of reading + 1 count)	
		$51M\Omega^{2}G\Omega$: ±(10% of reading + 1 count)	
500V≦V≦1200V	0.1MΩ~ 50.00GΩ	$0.1M\Omega^{-1}M\Omega : \pm (5\% \text{ of reading } + 3 \text{ count})$	
		$1 M\Omega^{\sim}500M\Omega$: ±(5% of reading + 1 count)	
		501MΩ~9.999GΩ:±(10% of reading + 1 count)	
		10GΩ~50GΩ: ±(20% of reading + 1 count)*	
Voltage Regulation		\pm (1% + 5V) [maximum rated load $ ightarrow$ no load]	
Voltmeter Accuracy		\pm (1% of reading + 5V)	
Short-Circuit Current		10mA max.	
Output Impedance		2kΩ	
Window Comparator Method		Yes	
RAMP UP (Rise Time)		0.1s~999.9s	
RAMP DOWN (Fall Time)		0.0s~999.9s	
TIMER (Test Time)*	1	OFF, 0.3s~999.9s	
TIMER (Test Time)*		±(100ppm + 20ms)	
WAIT TIME		0.0s~999.9s	
GND			
-		ON/OFF	
Ground Bond		02.004x22.004	
Output-Current		03.00A~32.00A ac	
Output-Current Resolution		0.01A	
Output-Current Accuracy		$3A \leq I \leq 8A \div \pm (1\% \text{ of reading} + 0.2A)$	
		8A <i≦ +="" 0.05a)<="" 32a∶±(1%="" of="" reading="" td=""></i≦>	
Test-Voltage		8Vac max (open circuit)	
GPT15000 Spec F1 doc		2 OF 3	

GPT15000_Spec_E1.doc

GOOD WILL INSTRUMENT CO., LTD.

N0. 7-1, Jhongsing Road, Tucheng Dist., New Taipei City, 236, Taiwan T (886) 2 2268-0389 F (886)2 2268-0639 www.gwinstek.com

L		
Test-Voltage Frequency	50Hz/60Hz selectable	
Ohmmeter Measurement Range	1mΩ~ 650mΩ	
Ohmmeter Measurement Resolution	0.1mΩ	
Ohmmeter Measurement Accuracy	\pm (1% of reading + 2 m Ω)	
Window Comparator Method	Yes	
TIMER (Test Time)	0.3s~999.9s	
TIMER Accuracy	±(100ppm + 20ms)	
Test Method	Four Terminal	
GND	ON/OFF	
Continuity Test		
Output-Current	100mA dc (fixed)	
Ohmmeter Measurement Range	0.10Ω~ 70.00Ω	
Ohmmeter Measurement Resolution	0.01Ω	
Ohmmeter Measurement Accuracy	$\pm(10\% \text{ of reading} + 2 \Omega)$	
Window Comparator Method	Yes	
TIMER (Test Time)*	0.3s~999.9s	
TIMER Accuracy	±(100ppm + 20ms)	
MEMORY		
Single Step Memory	MANU: 100 blocks	
Automatic Testing Memory	AUTO: 100 blocks, manu per auto: 10	
INTERFACE		
REMOTE (Front) terminal	Standard	
USB host (Front)	Standard	
Rear Output	Standard	
RS-232C	Standard	
USB device	Standard	
Signal I/O	Standard	
GPIB	Option	
LAN	Option	
DISPLAY		
	7" color LCD	
POWER SOURCE		
	AC 100V~240V ± 10%, 50Hz/60Hz	
DIMENSION & WEIGHT		
GPT-15001/15002/15003	380(W) x 148(H) x 492(D) mm; Approx. 17kg	
GPT-15004	380(W) x 148(H) x 546(D) mm; Approx. 21kg	

* When Ground Mode is "ON", the measurement range is 30GΩ max. and adding 10% error for accuracy.