TE Internal #: 5413558-2

RF Connectors, BNC RF Interface, Jack, RF Connector Mated Outer

Diameter (Approximate) .572 in [14.53 mm], 75 Ω , Bayonet, 2GHz

Operating Frequency

View on TE.com >




Connectors > RF Coax Connectors > RF Connectors > BNC RF Connector: Male (Jack), Right-angle, 75 Ohm, 2 Ghz











RF Interface: BNC

RF Connector Style: Jack

RF Connector Mated Outer Diameter (Approximate): 14.53 mm [.572 in]

Impedance: 75Ω

RF Connector Coupling Mechanism: Bayonet

All BNC RF Connector: Male (Jack), Right-angle, 75 Ohm, 2 Ghz (8)

Features

Product Type Features

RF Interface	BNC
RF Connector Style	Jack
Connector System	Cable-to-Board
Sealable	No
Connector & Contact Terminates To	Printed Circuit Board

Configuration Features

Number of Positions	1
PCB Mount Orientation	Right Angle
Number of Coaxial Contacts	1

Electrical Characteristics

Impedance	75 Ω	

Body Features

	Вос	y Insulation	Without
--	-----	--------------	---------



Body Shape	Circular
Body Material	Zinc
Body Plating Material	Tin
Contact Features	
RF Connector Center Contact Underplating Material	Nickel
	50 μin
RF Connector Center Contact Plating Material	Gold
RF Connector Center Contact Material	Beryllium Copper
Termination Features	
Termination Method to Printed Circuit Board	Through Hole - Solder
Termination Post & Tail Length	4.34 mm[.17 in]
Mechanical Attachment	
PCB Mount Retention	Without
RF Connector Coupling Mechanism	Bayonet
Connector Mounting Type	Board Mount
RF Contact Captivation Method	Mechanical
Detent	With
Dimensions	
RF Connector Mated Outer Diameter (Approximate)	14.53 mm[.572 in]
Height Above PC Board	10.97 mm[.432 in]
Usage Conditions	
Operating Temperature Range	-55 – 85 °C[-67 – 185 °F]
Operation/Application	
Operating Frequency	2 GHz
Packaging Features	
Packaging Method	Carton
Other	
Grade	Commercial
Dielectric Material	Polymethylpentene

Product Compliance

For compliance documentation, visit the product page on TE.com>



EU RoHS Directive 2011/65/EU	Compliant with Exemptions
EU ELV Directive 2000/53/EC	Compliant with Exemptions
China RoHS 2 Directive MIIT Order No 32, 2016	Restricted Materials Above Threshold
EU REACH Regulation (EC) No. 1907/2006	Current ECHA Candidate List: JAN 2021 (211) Candidate List Declared Against: JAN 2021 (211) SVHC > Threshold: Pb (.6% in Component part) Article Safe Usage Statements: Do not eat, drink or smoke when using this product. Wash thoroughly after handling. Recycle if possible and dispose of the article by following all applicable governmental regulations relevant to your geographic location.
Halogen Content	Low Bromine/Chlorine - Br and Cl < 900 ppm per homogenous material. Also BFR /CFR/PVC Free
Solder Process Capability	Wave solder capable to 265°C

Product Compliance Disclaimer

This information is provided based on reasonable inquiry of our suppliers and represents our current actual knowledge based on the information they provided. This information is subject to change. The part numbers that TE has identified as EU RoHS compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, mercury, PBB, PBDE, DBP, BBP, DEHP, DIBP, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2011/65/EU (RoHS2). Finished electrical and electronic equipment products will be CE marked as required by Directive 2011/65/EU. Components may not be CE marked. Additionally, the part numbers that TE has identified as EU ELV compliant have a maximum concentration of 0.1% by weight in homogenous materials for lead, hexavalent chromium, and mercury, and 0.01% for cadmium, or qualify for an exemption to these limits as defined in the Annexes of Directive 2000/53/EC (ELV). Regarding the REACH Regulation, the information TE provides on SVHC in articles for this part number is based on the latest European Chemicals Agency (ECHA) 'Guidance on requirements for substances in articles' posted at this URL: https://echa.europa.eu/guidance-documents/guidance-on-reach

Compatible Parts













TE Part # 5413589-3 KIT,PLUG,COML BNC,HEX CRP



TE Part # 5413959-3
BNC HEX RT ANG PLUG 50 OHM



TE Part # 5227079-5 COMM BNC PLUG



TE Part # 1-5221128-0
PLUG,COMMERCIAL BNC



TE Part # 5-1634514-1
BNC Str Jk Hex 75Ohm Nickel Pltd
RG59B/U



TE Part # 5413589-7 KIT,PLUG,COML BNC,HEX CRP



TE Part # 8-5227079-2 COMM BNC PLUG



TE Part # 5221199-5 JACK,75 OHM COML BNC



TE Part # 5227079-7 COMM. BNC-PLUG



TE Part # 1-5227079-9 COMM BNC PLUG



TE Part # 5-1634514-0
BNC Str Jk Hex 75Ohm Nickel Pltd
RG59B/U



TE Part # 5221185-8
PLUG,75 OHM,COMMERCIAL BNC



TE Part # 1-221128-0 PLUG,COMMERCIAL BNC



TE Part # 1-5221128-1
PLUG,COMMERCIAL BNC



TE Part # 1-5221185-5 PLUG,75 OHM,COML BNC




TE Part # 1-5221185-8
PLUG,75 OHM,COML BNC

Customers Also Bought



TE Part #1558667-1
PCB Power Relay: 30 amp, Monostable
DC



TE Part #1-770874-0 04P MINI UMNL HDR ASSY SN LF




TE Part #1-770858-0 10P MINI UMNL HDR ASSY SNDBL L




TE Part #1-826629-6 16X1 AMPMODU II HDR ST















Documents

Product Drawings

JACK,RTANG,PCB,75 OHM BNC

English

CAD Files

3D PDF

3D

3D PDF

English

Customer View Model

ENG_CVM_5413558-2_A.2d_dxf.zip

English

Customer View Model

ENG_CVM_5413558-2_A.3d_igs.zip

English

Customer View Model

ENG_CVM_5413558-2_A.3d_stp.zip

English

Customer View Model

ENG_CVM_CVM_5413558-2_D.2d_dxf.zip

English

Customer View Model

ENG_CVM_CVM_5413558-2_D.3d_igs.zip

English

Customer View Model

ENG_CVM_CVM_5413558-2_D.3d_stp.zip

English

RF Connectors, BNC RF Interface, Jack, RF Connector Mated Outer Diameter (Approximate) .572 in [14.53 mm], 75 Ω , Bayonet, 2GHz Operating Frequency



By downloading the CAD file I accept and agree to the **Terms and Conditions** of use.

Datasheets & Catalog Pages

BNC Connectors

English

Product Specifications

Product Specification

English

Agency Approvals

UL Report

English