# SUPERTRONIC®-C-PVC

# colour code DIN 47100, EMC-preferred type





HELUKABEL® SUPERTRONIC®-C-PVC 4x0,25 QMM / 49633 350 V C€

#### **TECHNICAL DATA**

PVC drag chain cable in alignment with DIN VDE 0285-525-1 / DIN EN 50525-1

Temperature range flexible  $-5^{\circ}\text{C to } +70^{\circ}\text{C}$ fixed  $-40^{\circ}\text{C to } +70^{\circ}\text{C}$ 

Nominal voltage AC U 350 V Test voltage core/core 1500 V Breakdown voltage 3000 V

**Coupling resistance** at 30 MHz, approx. 250 Ohm/

km

**Minimum bending radius** flexible 7.5x Outer-Ø fixed 4x Outer-Ø

### CABLE STRUCTURE

- · Copper wire bare, extra finely stranded
- · Wire structure:

0.14 mm<sup>2</sup>: approx. 18 x 0.10 mm 0.25 mm<sup>2</sup>: approx. 32 x 0.10 mm 0.34 mm<sup>2</sup>: approx. 42 x 0.10 mm

- Core insulation: PVC acc. to DIN VDE 0207-363-3 / DIN EN 50363-3 (compound type TI2)
- Core identification acc. to DIN 47100, colour coded
- x = without protective conductor
- · Cores stranded in layers with optimally matched lay lengths
- · Fleece wrapping
- Screen: braided screen of tinned copper, approx. coverage 85%
- Outer sheath: Special-PVC acc. to DIN VDE 0207-363-4-1 / DIN EN 50363-4-1 (compound type TM2)
- Sheath colour: grey (RAL 7001)
- Length marking: in metres

## PROPERTIES

- largely resistant to: oil, for details, see "Technical Information"
- low adhesion
- suitable for use in drag chains
- the materials used during manufacturing are cadmium-free, contain no silicone and are free from substances harmful to the wetting properties of lacquers

#### TESTS

 flame-retardant acc. to DIN VDE 0482-332-1-2 / DIN EN 60332-1-2 / IEC 60332-1-2

#### APPLICATION

These cables are ideal for the use in drag chain applications; for frequent lifting and bending stress in machine and tool construction, in robotics and on permanently moving machine parts. A long service life also guarantees reliable function and high efficiency. EMC= Electromagnetic Compatibility; in order to optimise EMC properties, we recommend a double-sided and all-round large contact area of the copper braiding.

# NOTES

- the conductor is metrically (mm²) constructed, AWG numbers are approximated, and are for reference only
- for use in energy supply systems:
  - 1) the assembly instructions must be observed
- 2) for further application parameters, please refer to the selection tables
- 3) for special applications, we recommend contacting us and using our data entry form for energy supply systems

Part no.	No. cores x cross-sec. mm²	AWG, approx.	Outer Ø mm, approx.	Cu-weight kg/km	Weight kg/km, approx.
49620	2 x 0.14	26	3.9	11.2	33.0
49621	3 x 0.14	26	4.3	14.1	36.0
49622	4 x 0.14	26	4.6	15.5	41.0
49623	5 x 0.14	26	4.9	18.3	46.0
49624	7 x 0.14	26	5.7	27.6	70.0
49625	10 x 0.14	26	6.6	39.3	88.0
49626	12 x 0.14	26	6.6	41.1	97.0
49627	14 x 0.14	26	7.1	45.3	105.0
49628	18 x 0.14	26	7.7	54.1	122.0
49629	24 x 0.14	26	8.9	66.3	156.0
49630	25 x 0.14	26	9.5	68.4	162.0
49631	2 x 0.25	24	4.6	14.9	39.0
49632	3 x 0.25	24	4.8	18.8	45.0
49633	4 x 0.25	24	5.2	21.3	52.0
49634	5 x 0.25	24	5.8	31.0	70.0
49635	7 x 0.25	24	6.6	39.6	88.0
49636	10 x 0.25	24	7.8	53.9	114.0

Part no.	No. cores x cross-sec. mm²	AWG, approx.	Outer Ø mm, approx.	Cu-weight kg/km	Weight kg/km, approx.
49637	12 x 0.25	24	7.8	59.1	128.0
49638	14 x 0.25	24	8.4	64.2	140.0
49639	18 x 0.25	24	9.2	78.4	166.0
49640	24 x 0.25	24	10.8	89.9	210.0
49641	25 x 0.25	24	11.2	101.0	220.0
49642	2 x 0.34	22	5.0	16.1	46.0
49643	3 x 0.34	22	5.3	28.7	62.0
49644	4 x 0.34	22	5.9	35.7	80.0
49645	5 x 0.34	22	6.3	39.1	88.0
49646	7 x 0.34	22	7.5	52.7	116.0
49647	10 x 0.34	22	8.9	67.4	156.0
49648	12 x 0.34	22	8.9	76.4	167.0
49649	14 x 0.34	22	9.5	85.3	195.0
49650	18 x 0.34	22	10.4	99.7	225.0
49651	24 x 0.34	22	12.2	147.1	312.0
49652	25 x 0.34	22	12.7	155.0	325.0

