## **SIEMENS**

## **Data sheet**

6EP3334-7SC00-3AX0



## SITOP PSU6200/1AC/DC24V/10A/EX

SITOP PSU6200 Ex 24 V/10 A stabilized power supply input: 120/230 V AC output: 24 V / 10 A DC with diagnostic interface with painted printed circuit boards

Figure similar

Input	
type of the power supply network	1-phase AC or DC
supply voltage at AC	
minimum rated value	120 V
maximum rated value	240 V
• initial value	85 V
• full-scale value	264 V
supply voltage	
• at DC	110 240 V
input voltage	
• at DC	85 275 V
design of input wide range input	Yes
overvoltage overload capability	300 V AC for 30 s
operating condition of the mains buffering	at Vin = 240 V
buffering time for rated value of the output current in the event of power failure minimum	45 ms
operating condition of the mains buffering	at Vin = 240 V
line frequency	
1 rated value	50 Hz
2 rated value	60 Hz
line frequency	47 63 Hz
input current	
<ul> <li>at rated input voltage 120 V</li> </ul>	2.2 A
<ul> <li>at rated input voltage 240 V</li> </ul>	1.2 A
current limitation of inrush current at 25 °C maximum	6 A
fuse protection type	5 A
• in the feeder	Circuit breaker from 4 A characteristic C/6 A characteristic B to 10 A characteristic C or circuit breaker 3RV2011-1EA10 (setting 4 A) or 3RV2711-1ED10 (UL 489)
Output	
voltage curve at output	Controlled, isolated DC voltage
number of outputs	1
output voltage at DC rated value	24 V
output voltage	
at output 1 at DC rated value	24 V
relative overall tolerance of the voltage	3 %
relative control precision of the output voltage	
<ul> <li>on slow fluctuation of input voltage</li> </ul>	0.1 %
<ul> <li>on slow fluctuation of ohm loading</li> </ul>	0.1 %
residual ripple	

	20 \
• maximum	30 mV
• typical	20 mV
voltage peak	
• maximum	30 mV
• typical	20 mV
adjustable output voltage	24 28 V
product function output voltage adjustable	Yes
type of output voltage setting	via potentiometer; max. 240 W (288 W up to 45°C)
display version for normal operation	Green LED for 24 V OK
type of signal at output	Electronic contact (NO contact, contact rating 30 V DC/0.1 A) for DC O.K. or diagnostic interface
behavior of the output voltage when switching on	Overshoot of Vout < 2 %
response delay maximum	0.5 s
voltage increase time of the output voltage	
• typical	200 ms
output current	
rated value	10 A
rated range	0 10 A; 12 A up to +45°C; +60 +70 °C: Derating 3%/K
supplied active power typical	240 W
short-term overload current	
on short-circuiting during the start-up typical	12 A
at short-circuit during operation typical	12 A
product feature	
parallel switching of outputs	can be set with DIP switch
bridging of equipment	Yes; switchable characteristic
number of parallel-switched equipment resources for increasing the power	2
Efficiency	
efficiency in percent	92.8 %
power loss [W]	0210 //
at rated output voltage for rated value of the output	18 W
current typical	
<ul> <li>during no-load operation maximum</li> </ul>	2.2 W
Closed-loop control	
relative control precision of the output voltage at load step of	2 %
resistive load 10/90/10 % typical	
setting time	
<ul> <li>load step 10 to 90% typical</li> </ul>	2 ms
<ul> <li>load step 90 to 10% typical</li> </ul>	2 ms
• maximum	3 ms
Protection and monitoring	
design of the overvoltage protection	< 32 V
• typical	12 A
property of the output short-circuit proof	Yes
design of short-circuit protection	Shutdown and periodic restart attempts
overcurrent overload capability in normal operation	overload capability 150 % lout rated up to 5 s/min
Safety	
galvanic isolation between input and output	Yes
galvanic isolation	Safety extra low output voltage Vout according to EN 60950-1
operating resource protection class	Class I
leakage current	
maximum	3.5 mA
protection class IP	IP20
Approvals	
certificate of suitability	Voc
CE marking	Yes Vaccalli va Listed (III, 500, CCA, CC2, 2 No. 407.4). File F407250; aCCA, cc
UL approval	Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus (CSA C22.2 No. 60950-1, UL 60950-1)
CSA approval	Yes; cULus-Listed (UL 508, CSA C22.2 No. 107.1), File E197259; cCSAus
	(CSA C22.2 No. 60950-1, UL 60950-1)
	(
• cCSAus, Class 1, Division 2	No
<ul><li>cCSAus, Class 1, Division 2</li><li>ATEX</li></ul>	

certificate of suitability	
<ul> <li>relating to ATEX</li> </ul>	IECEx Ex ec nC IIC T3 Gc; ATEX (EX) II 3G Ex ec nC IIC T3 Gc
• IECEx	Yes; IECEx Ex ec nC IIC T3 Gc
NEC Class 2	No
<ul> <li>ULhazloc approval</li> </ul>	No
FM registration	No
certificate of suitability shipbuilding approval	Yes
shipbuilding approval	ABS; in process: DNV
Marine classification association	
<ul> <li>American Bureau of Shipping Europe Ltd. (ABS)</li> </ul>	Yes
<ul> <li>French marine classification society (BV)</li> </ul>	No
DNV GL	No
<ul> <li>Lloyds Register of Shipping (LRS)</li> </ul>	No
Nippon Kaiji Kyokai (NK)	No
EMC	
standard	
for emitted interference	EN 55022 Class B
<ul> <li>for mains harmonics limitation</li> </ul>	EN 61000-3-2
<ul> <li>for interference immunity</li> </ul>	EN 61000-6-2
environmental conditions	
ambient temperature	
during operation	-30 +70 °C; with natural convection a monotonically increasing start-up from -25 °C, safe start-up from -40 °C
during transport	-40 +85 °C
during storage	-40 +85 °C
environmental category according to IEC 60721	Climate class 3K3, 5 95% no condensation
Mechanics	
type of electrical connection	push-in terminals
• at input	L1/+, L2/N/-, PE: push-in for 0.5 4 mm² single-core/finely stranded
• at output	+1, +2, -1, -2, -3: push-in for 0.5 2.5 mm <sup>2</sup>
for auxiliary contacts	13, 14 (alarm signal): 1 push-in terminal each for 0.2 1.5 mm <sup>2</sup>
width of the enclosure	45 mm
height of the enclosure	135 mm
depth of the enclosure	125 mm
required spacing	
• top	45 mm
• bottom	45 mm
● left	0 mm
• right	0 mm
net weight	0.9 kg
product feature of the enclosure housing can be lined up	Yes
fastening method	Snaps onto DIN rail EN 60715 35x7.5/15
electrical accessories	Buffer module, redundancy module
mechanical accessories	Identification labels SIMATIC ET 200SP 6ES7193-6LF30-0AW0
other information	Specifications at rated input voltage and ambient temperature +25 °C (unless
	otherwise specified)

