## **SIEMENS**

## **Data sheet**

## 6ES7136-6CB00-0CA0



SIMATIC ET 200SP, F-TM Count 1x1Vpp sin/cos HF, PROFIsafe, 1 channel, for incremental rotary encoders, sin/cos 1 Vpp, suitable for BU type A0, pack quantity: 1 unit

General information	
Product type designation	F-TM Count 1x1Vpp sin/cos HF
Firmware version	V1.0
FW update possible	Yes
usable BaseUnits	BU type A0
Color code for module-specific color identification plate	CC01
Product function	
● I&M data	Yes; I&M0 to I&M3
Engineering with	
STEP 7 TIA Portal configurable/integrated from version	Step 7 V17 or higher: use GSDML for prior versions
Supply voltage	
power supply according to NEC Class 2 required	No
Load voltage L+	
Rated value (DC)	24 V
<ul> <li>permissible range, lower limit (DC)</li> </ul>	20.4 V
<ul> <li>permissible range, upper limit (DC)</li> </ul>	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	50 mA; without load, 150 mA with 300 mA encoder load
Encoder supply	
5 V encoder supply	
• 5 V	Yes; 5.1 V ±3.5 %
Short-circuit protection	Yes; Electronic overload protection; no protection on applying a normal or counter voltage.
Output current, max.	300 mA
Power loss	
Power loss, typ.	1.25 W
Address area	
Address space per module	
• Inputs	14 byte; S7-300/400F CPU, 13 byte
Outputs	5 byte; S7-300/400F CPU, 4 byte
Hardware configuration	
Automatic encoding	Yes
Electronic coding element type H	Yes
Digital inputs	
Number of digital inputs	1; (counter input)
Digital inputs, parameterizable	Yes
Digital input functions, parameterizable	
Gate start/stop	Yes
Counter for incremental encoder	Yes

— Number, max.	1
Input voltage	
Type of input voltage	sin/cos 1 Vpp
Input delay (for rated value of input voltage)	
Minimum pulse width for program reactions	2.5 μs for parameterization "none"
for technological functions	
— parameterizable	Yes
Cable length	
• shielded, max.	150 m
Encoder	
Connectable encoders	
Incremental encoder (symmetrical)	Yes; up to 200 kHz depending on cable type and length
Encoder signals, incremental encoder (symmetrical)	
Input voltage	1 Vpp, centered at 2.5 V offset
Input frequency, max.	200 kHz
<ul> <li>Counting frequency, max.</li> </ul>	800 kHz; with quadruple evaluation
<ul> <li>Cable length, shielded, max.</li> </ul>	150 m
• Incremental encoder with A/B tracks, 90° phase offset	Yes; sin/cos
<ul> <li>Incremental encoder with A/B tracks, 90° phase offset and zero track</li> </ul>	Yes; sin/cos/zero
Interrupts/diagnostics/status information	
Diagnostics function	Yes; see chapter "Diagnostic Messages" in the manual
Alarms	, and a second s
Diagnostic alarm	Yes
Hardware interrupt	No
Diagnoses	
Monitoring the supply voltage	Yes
Wire-break	Yes
Short-circuit	Yes
A/B transition error at incremental encoder	Yes
Diagnostics indication LED	
• RUN LED	Yes; green LED
• ERROR LED	Yes; red LED
<ul> <li>Monitoring of the supply voltage (PWR-LED)</li> </ul>	Yes; green LED
Channel status display	Yes; green LED
for channel diagnostics	Yes; red LED
for module diagnostics	Yes; green/red DIAG LED
Integrated Functions	
Counter	Yes
Number of counters	1
Counting frequency, max.	800 kHz; with quadruple evaluation
Safety monitoring functions	
Safe Operating Stop (SOS)	Yes
Safety-Limited Speed (SLS)	Yes
Safe Direction (SDI)	Yes
Safe Speed Monitor (SSM)	Yes
Counting functions	
Continuous counting	Yes
Counter response parameterizable	Yes
Software gate	Yes
Counting range, parameterizable	Yes
Measuring functions	
Measuring range	
Frequency measurement, min.	0.04 Hz
Frequency measurement, max.	
• •	800 kHz; with quadruple evaluation
Cycle duration measurement, min.  Cycle duration measurement, may	1 µs
Cycle duration measurement, max.  Valority measurement, min.	25 s
Velocity measurement, min.	0 (speed in configured units per selected time basis - speed*1 000)
— Velocity measurement, max.	2 147 483 (speed in configured units per selected time basis - speed*1 000)
Accuracy	up to 100 name depending on recognising interval and discontinuous
Frequency measurement	up to 100 ppm; depending on measuring interval and signal evaluation; at low

frequency external noise may have an effect on accuracy (reference the graph in 2.2.3)
up to 100 ppm; depending on measuring interval and signal evaluation; at low frequency external noise may have an effect on accuracy (reference the graph in 2.2.3)
up to 100 ppm; depending on measuring interval and signal evaluation; at low frequency external noise may have an effect on accuracy (reference the graph in 2.2.3)
No; Only one channel is available
Yes
No
No
707 V DC (type test)
Yes
Cat. 4, PLe
SIL 3
e of 100 hours)
< 2.00E-03 signal monitoring disabled
< 3.00E-05
< 3.00E-08 1/h signal monitoring disabled
< 1.00E-09 1/h
0 °C
60 °C
0 °C
55 °C
On request: Installation altitudes greater than 2 000 m
15 mm
73 mm
58 mm
42 g

6ES71366CB000CA0 Page 3/3

last modified:

12/28/2021