3-447-257-03 1/8.24



METRALINE EVSE IT (Z525M)

1-/3-PHASE TEST ADAPTER FOR TESTING THE EFFECTIVENESS OF PROTECTIVE MEASURES AT E-CHARGING POINTS FOR THE METRALINE MF

- Type 2 plug
- Simulation of CP states A, B, C and E per DIN EN IEC 61851-1 / VDE 0122-1
- Direct connection to and versatile application options in combination with the METRALINE MF installation tester
- Long test cable (1.5 m)
- Convenient and safe adaptation to AC charging points
- Simple operation, perfectly matched to the way you work



APPLICATION

METRALINE EVSE IT is a test adapter (accessory) which supports all relevant measurements to be performed with the METRALINE MF installation tester. It is connected between the EVSE charging point (type 2 plug) and the measuring inputs of the METRALINE MF. All wires of the charging plug are available: L1, L2, L3, N, PE, CP and PP.

The following typical measurements can be performed: voltage, frequency, phase display, phase sequence, various RCD tests and measurements, insulation resistance, low-resistance measurements, line and loop impedance, etc.

SCOPE OF DELIVERY

Standard Scope of Delivery:

- 1 METRALINE EVSE IT
- 1 Operating Instructions

ASSOCIATED MEASURING/ TEST INSTRUMENT

METRALINE MF (M520F) – Multifunctional installation tester for standards-compliant testing in electrical systems and installations in accordance with IEC 60364-6 (DIN VDE 0100-600), DIN EN 50110-1 (DIN VDE 0105-100), IEC 61851-1 (DIN VDE 0122-1) and the corresponding sections of EN 61557 (VDE 0413).

TECHNICAL DATA

Input voltage:	230 V / 400 V 3~ 50/60 Hz	CP simulation	Mode A, B, C
Measuring category:	CAT II 300 V	Fault simulation:	CP fault "E"
Current-carrying capacity:	max. 10 A	Operating temperatures:	0 +40 °C
Fixed terminals at the measuring/ test instrument:	4 mm safety plugs	Storage temperatures:	–10 +50 °C
Charging plug:	IEC 62196-2 type 2 plug	Humidity:	0 80 % relative humidity
Length of test cable:	1.5 m	Protection category:	IP 40
PP simulation:	configured internally for 32 A	Compliance with:	DIN EN 61010-1 / DIN EN 61010-031



© Gossen Metrawatt GmbH Prepared in Germany • Subject to change without notice / errors excepted • A pdf version is available on the Internet

All trademarks, registered trademarks, logos, product names, and company names are the property of their respective owners.

YOUR CONTACT PARTNER

Gossen Metrawatt GmbH Südwestpark 15 90449 Nürnberg Germany



+49 911 8602-0



+49 911 8602-669



info@gossenmetrawatt.com



www.gossenmetrawatt.com