

SKU# 120894

Lucci LEDlux

This GX53 lamp has 3 pre set scenes called Day night and sleep, it is controlled via a mechanical or relay ON/OFF switch. It is not compatible with rotary or touch button dimmer switches.

This lamp incorporates 3 light level and colour temperature combinations that have been specifically designed to work with your circadian rhythm.

Switching cycle

Switching the lamp on / off within 2-3 seconds will cycle the lamp through the below pattern.

FIRST SWITCH 2700K 350LM –(Sleep) recommended setting for at least 2 hours before bed.

SECOND SWITCH 2700K 1700LM – (Night) recommended setting 6 hours before bed.

THIRD SWITCH 4000K 1800LM – **(Day)** recommended setting at wake and throughout the bulk of your day.

Switching twice immediately (within 1 second) will return the lamp directly to default first switch setting - 2700K 350lm

The lamp contains a memory feature that activates after remaining on for more than 7 seconds. This will ensure the lamp returns to your last active setting.

At shipping – your new lamp has been set to the default first switch setting.

Lucci LEDLux is trademark Brightlite Nominees Pty. Ltd. of 140 Fulton Drive Derrimut Vic 3026 Australia.

SKU# 120894



Size of the GX53 lamp: D:200 mm x H:47 mm

Weight of the GX53 lamp: 0.3 kg

NOTE: Check and ensure the size of the lamp is suitable for the luminaire. If this lamp is for replacing the existing lamp of the luminaire, ensure the size and the weight of the lamp is not significantly higher than the existing one.

Increased weight may reduce the mechanical stability of the certain luminaires and lamp holders and may impair the contact making and lamp retention.

NOTE: This lamp is only compatible with Lucci products. Check the instruction manual of the Lucci products for more details.

Lucci LEDLux is trademark Brightlite Nominiees Pty. Ltd. of 140 Fulton Drive Derrimut Vic 3026 Australia.