




Power Inverter 200W TE21

For mobile use of various electronic devices via 12V connection



 Spannungswandler DC 12V auf AC 230V / Power Inverter DC 12V to AC 230V

 1 USB-A 5V max. 2,4A / 1 x USB-A 5V max. 2,4A

 1 x USB-C max. 12V max. 3A / 1 x USB-C max. 12V max 3A

 Über- & Unterspannungsschutz / High & Low Voltage Protection

 230V Steckdose / 230V Socket

 Eingebaute Ventilationskühlung / Built-in Ventilation Fan

 200W kontinuierliche Ausgangsleistung / 200W continuously Output Power

 Überlastungsschutz / Overcurrent Protection

 Abschaltautomatik / Automatic Turn Off

 Modifizierte Sinuswelle / Modified sine wave

- For mobile use of electronic devices via 12V connection
- 1 x USB-C max. 12V max 3A 1 xUSB-A 5V max. 2,4A
- 230V safety contact socket
- Converts 12V DC battery power into standard 230V AC (household) power, to run a variety of electronics, e.g. tablets, smartphones, laptop computers, game systems, TVs, DVD/MP3 players, camping accessories, GPS units and much more
- Output power max. 200W (continuous) & 400W (peak)
- Automatic safety shutdown to secure the car battery
- Protection against overload
- Overheating protection through built-in ventilation

Technical specifications:

- Input voltage of the battery DC 12V (10.2V–15,8V)
- Output voltage AC 230V / AC frequency 50Hz nominal
- Modified sine wave
- Circuit protection (DC overload):25A internal fuses
- Cable length 90cm
- Weight / Dimensions:0,33 kg / (L) 17,9 x (B) 6,4 x (H) 5,2cm

Package Contents:

Power Inverter 200W TE21, User Manual



Article-No. 4855

